



System Fact Sheet

SYSTEM	POWER	PORTS
<p>Introduced: July 1997 Discontinued: August 1998 Gestalt ID: Form Factor: SuperMac C600 Weight (lbs.): 16 Dimensions (inches): 16 H x 6.75 W x 15.5 D</p> <p>Codename: Order Number: KB Article #:</p> <p><i>Called the Apus 3000 in the UK</i></p>	<p>Max. Watts: Amps: BTU Per Hour: Voltage Range: 100-240 V Freq'y Range (Hz): 50-60 Hz Battery Type: 3.6V lithium</p> <p><input type="checkbox"/> Soft Power <input type="checkbox"/> Monitor Power Outlet</p>	<p>ADB: 1 Video: DB-15 Floppy: none SCSI: DB-25</p> <p>GeoPort Connectors: 2 Ethernet: 10Base-T PCI</p> <p>Microphone Port Type:</p> <p><input type="checkbox"/> Printer <input checked="" type="checkbox"/> Speaker <input type="checkbox"/> Modem <input checked="" type="checkbox"/> Headphone <input type="checkbox"/> Airport <input type="checkbox"/> Remote Control</p>

VIDEO	Built-in Display:	Maximum Color Bit-depth ¹ At:
VRAM Speed:	VRAM Needed:	512 640 640 640 800 832 1024 1152 1280
	Video Configuration:	x384 x400 x480 x870 ² x600 x624 x768 x870 x1024
	VRAM	16 8
	VRAM	
	1MB	
	2MB PCI card option	

¹ 1-bit = Black & White; 2-bit = 4 colors; 4-bit = 16 colors; 8-bit = 256 colors; 16-bit = Thousands; 24-bit = Millions
² The maximum color depth listed for 640x870 is 8-bit, reflecting the capabilities of the Apple 15" Portrait Display.

LOGICBOARD	MEMORY
<p>Main Processor: 603e, 280 MHz PMMU: none FPU: none Data Path: , 40 MHz L1 Cache: 32K L2 Cache: 256K-1MB Secondary Processor: none Slots: 3 PCI</p>	<p>Memory on Logic Board: 16MB Minimum RAM: 16 or 32 Maximum RAM: 144 MB RAM Slots: 2 168-pin Minimum RAM Speed: 70 ns RAM Sizes: 32, 64 MB Install in Groups of: 1</p> <p><i>(16 MB on motherboard), expandable to 144 MB using two 168-pin DIMMs and 70ns or faster 5 volt EDO or fast-page (FPM) DRAM. When upgrading RAM, avoid 4K refresh memory, choosing 2K memory</i></p>

SOFTWARE	Supported Macintosh System Software:
<p><input type="checkbox"/> Speech Recognition Supported</p> <p>Addressing Modes: 32-bit Original SSW: 7.5.3 Original Enabler:</p> <p>ROM ID: ROM Version: ROM Size: AppleTalk Version:</p>	<p><input type="checkbox"/> A/UX 1.0 <input type="checkbox"/> NOS 1.11 <input type="checkbox"/> ProDOS <input type="checkbox"/> <input type="checkbox"/> A/UX 1.11 <input type="checkbox"/> NOS 1.3 <input type="checkbox"/> GS/OS <input type="checkbox"/> <input type="checkbox"/> A/UX 2.0 <input type="checkbox"/> NOS 2.0 <input type="checkbox"/> NeXTStep 1.x <input type="checkbox"/> <input type="checkbox"/> A/UX 3.0.1 <input type="checkbox"/> NOS 2.1 <input type="checkbox"/> NeXTStep 2.x <input type="checkbox"/> <input type="checkbox"/> A/UX 4.1.4 <input type="checkbox"/> LOS 7/7 <input type="checkbox"/> NeXTStep 3.x <input type="checkbox"/> <input type="checkbox"/> A/UX 4.1.4.1 <input type="checkbox"/> DOS 3.1 <input type="checkbox"/> OpenStep <input type="checkbox"/> <input type="checkbox"/> A/UX 4.1.5 <input type="checkbox"/> SOS 1.3 <input type="checkbox"/> <1.0 <input type="checkbox"/></p>

SOUND	STORAGE
<p><input type="checkbox"/> Built-in Microphone</p> <p>Microphone Port Type: Sound In: stereo, 16-bit Sound Out: stereo, 16-bit</p>	<p><input checked="" type="checkbox"/> Supports Internal CD-ROM</p> <p>Floppy Size: 1.44MB Floppy Inject: manual Internal HD Size: 1.2, 4GB Internal HD Interface: Original CD-ROM Speed: 8-24x</p> <p><i>The version of FWB Hard Disk Toolkit that ships with the SuperMac may not be compatible with Mac OS 8 or later. You must use version</i></p>

HISTORY

The C600 was Umax's least expensive minitower. Initially introduced at 140 MHz, by the end of the line Umax was selling 280 MHz models. The C600 was designed around a modified Tanzania motherboard. An internal ZIP drive was also available as an option.

The C600 was the first clone to incorporate an inline cache, which Umax called CacheDoubler.