



System Fact Sheet

<p>SYSTEM</p> <p>Introduced: October 1997 Discontinued: August 1998 Gestalt ID: Form Factor: SuperMac C500 Weight (lbs.): 28 Dimensions (inches): 6.5 H x 16.5 W x 17.25 D</p> <p>Codename: Oder Number: KB Article #:</p>	<p>POWER</p> <p>Max. Watts: Amps: BTU Per Hour: Voltage Range: 100-240 V Freq'y Range (Hz): 50-60 Hz Battery Type: 3.6V lithium <input type="checkbox"/> Soft Power <input type="checkbox"/> Monitor Power Outlet</p>	<p>PORTS</p> <p>ADB: 1 Video: DB-15 Floppy: none SCSI: DB-25 GeoPort Connectors: 2 Ethernet: 10Base-T PCI</p> <p>Microphone Port Type: <input type="checkbox"/> Printer <input checked="" type="checkbox"/> Speaker <input type="checkbox"/> Modem <input checked="" type="checkbox"/> Headphone <input type="checkbox"/> Airport <input type="checkbox"/> Remote Control</p>
---	---	--

VIDEO

Built-in Display:	<i>Maximum Color Bit-depth¹ At:</i>									
VRAM Speed:	512	640	640	640	800	832	1024	1152	1280	
VRAM Needed:	x384	x400	x480	x870 ²	x600	x624	x768	x870	x1024	
VRAM:										24
Video Configuration:	4MB									

¹ 1-bit = Black & White; 2-bit = 4 colors; 4-bit = 16 colors; 8-bit = 256 colors; 16-bit = Thousands; 24-bit = Millions
² The maximum color depth listed for 640x870 is 8-bit, reflecting the capabilities of the Apple 15" Portrait Display.

xMicro Twin Turbo Graphics Accelerator

<p>LOGICBOARD</p> <p>Main Processor: 604e, 233 MHz PMMU: none FPU: none Data Path: , 40 MHz L1 Cache: 32K L2 Cache: 512K-1MB Secondary Processor: none Slots: 2PCI</p>	<p>MEMORY</p> <p>Memory on Logic Board: 16MB Minimum RAM: 24MB Maximum RAM: 144MB RAM Slots: 3 168-pin Minimum RAM Speed: 70 ns RAM Sizes: 32, 64, 128 MB Install in Groups of: 1</p> <p><i>(16 MB on motherboard), expandable to 144 MB using two 168-pin DIMMs and 70ns or faster 5 volt EDO or fast-page (FPM) DRAM. When upgrading RAM, avoid 4K refresh memory, choosing 2K memory</i></p>
--	---

<p>SOFTWARE</p> <p><input type="checkbox"/> Speech Recognition Supported</p> <p>Addressing Modes: 32-bit Original SSW: 7.5.3 Original Enabler:</p>	<p>ROM ID: ROM Version: ROM Size: AppleTalk Version:</p>	<p>Supported Macintosh System Software:</p> <table border="0"> <tr> <td><input type="checkbox"/> A/UX 1.0</td> <td><input type="checkbox"/> NOS 1.11</td> <td><input type="checkbox"/> ProDOS</td> <td><input type="checkbox"/></td> </tr> <tr> <td><input type="checkbox"/> A/UX 1.11</td> <td><input type="checkbox"/> NOS 1.3</td> <td><input type="checkbox"/> GS/OS</td> <td><input type="checkbox"/></td> </tr> <tr> <td><input type="checkbox"/> A/UX 2.0</td> <td><input type="checkbox"/> NOS 2.0</td> <td><input type="checkbox"/> NeXTStep 1.x</td> <td><input type="checkbox"/></td> </tr> <tr> <td><input type="checkbox"/> A/UX 3.0.1</td> <td><input type="checkbox"/> NOS 2.1</td> <td><input type="checkbox"/> NeXTStep 2.x</td> <td><input type="checkbox"/></td> </tr> <tr> <td><input type="checkbox"/> A/UX 4.1.4</td> <td><input type="checkbox"/> LOS 7/7</td> <td><input type="checkbox"/> NeXTStep 3.x</td> <td><input type="checkbox"/></td> </tr> <tr> <td><input type="checkbox"/> A/UX 4.1.4.1</td> <td><input type="checkbox"/> DOS 3.1</td> <td><input type="checkbox"/> OpenStep</td> <td><input type="checkbox"/></td> </tr> <tr> <td><input type="checkbox"/> A/UX 4.1.5</td> <td><input type="checkbox"/> SOS 1.3</td> <td><input type="checkbox"/> <1.0</td> <td><input type="checkbox"/></td> </tr> </table>	<input type="checkbox"/> A/UX 1.0	<input type="checkbox"/> NOS 1.11	<input type="checkbox"/> ProDOS	<input type="checkbox"/>	<input type="checkbox"/> A/UX 1.11	<input type="checkbox"/> NOS 1.3	<input type="checkbox"/> GS/OS	<input type="checkbox"/>	<input type="checkbox"/> A/UX 2.0	<input type="checkbox"/> NOS 2.0	<input type="checkbox"/> NeXTStep 1.x	<input type="checkbox"/>	<input type="checkbox"/> A/UX 3.0.1	<input type="checkbox"/> NOS 2.1	<input type="checkbox"/> NeXTStep 2.x	<input type="checkbox"/>	<input type="checkbox"/> A/UX 4.1.4	<input type="checkbox"/> LOS 7/7	<input type="checkbox"/> NeXTStep 3.x	<input type="checkbox"/>	<input type="checkbox"/> A/UX 4.1.4.1	<input type="checkbox"/> DOS 3.1	<input type="checkbox"/> OpenStep	<input type="checkbox"/>	<input type="checkbox"/> A/UX 4.1.5	<input type="checkbox"/> SOS 1.3	<input type="checkbox"/> <1.0	<input type="checkbox"/>
<input type="checkbox"/> A/UX 1.0	<input type="checkbox"/> NOS 1.11	<input type="checkbox"/> ProDOS	<input type="checkbox"/>																											
<input type="checkbox"/> A/UX 1.11	<input type="checkbox"/> NOS 1.3	<input type="checkbox"/> GS/OS	<input type="checkbox"/>																											
<input type="checkbox"/> A/UX 2.0	<input type="checkbox"/> NOS 2.0	<input type="checkbox"/> NeXTStep 1.x	<input type="checkbox"/>																											
<input type="checkbox"/> A/UX 3.0.1	<input type="checkbox"/> NOS 2.1	<input type="checkbox"/> NeXTStep 2.x	<input type="checkbox"/>																											
<input type="checkbox"/> A/UX 4.1.4	<input type="checkbox"/> LOS 7/7	<input type="checkbox"/> NeXTStep 3.x	<input type="checkbox"/>																											
<input type="checkbox"/> A/UX 4.1.4.1	<input type="checkbox"/> DOS 3.1	<input type="checkbox"/> OpenStep	<input type="checkbox"/>																											
<input type="checkbox"/> A/UX 4.1.5	<input type="checkbox"/> SOS 1.3	<input type="checkbox"/> <1.0	<input type="checkbox"/>																											

<p>SOUND</p> <p><input type="checkbox"/> Built-in Microphone</p> <p>Microphone Port Type: Sound In: stereo, 16-bit Sound Out: stereo, 16-bit</p>	<p>STORAGE</p> <p><input checked="" type="checkbox"/> Supports Internal CD-ROM</p> <p>Floppy Size: 1.44MB Floppy Inject: manual Internal HD Size: Internal HD Interface: Original CD-ROM Speed: 24x</p> <p><i>The version of FWB Hard Disk Toolkit that ships with the SuperMac may not be compatible with Mac OS 8 or later. You must use version</i></p>
---	---

HISTORY

The J710 was the last new model from Umax -- and only about 50 were ever produced. Combining the form factor of the compact C500 (below monitor in photo) with the power of 604e or G3 , the J710 would have been great for power users on a budget. About 90% shipped with the 200 MHz 604e. The G3 models were for internal use only.

Although Apple certified the model for sale, their refusal to renew Umax's license to produce Macclones lead Umax to abandon the J710.

The J710 looks just like the C500, the computer beneath the monitor in this photo. It also uses the same ZIP (or PEZ) socket for processor