

Logic Board

Name	Processor	Speed	PMMU	FPU	Data Path Speed	Data Path Size	Caches			Secondary Processor	Slots
							L1	L2	L3		
Apple I	MOS	1 MHz	none	none	1 MHz	8-bit	n/a	n/a		n/a	
Apple II	MOS	1 MHz	none	none	1 MHz	8-bit	n/a	n/a		n/a	8 proprietary
Apple II+	MOS	1 MHz	none	none	1 MHz	8-bit	n/a	n/a		n/a	8 proprietary
Apple II+ (Bell & Howell)	MOS	1 MHz	none	none	1 MHz	8-bit	n/a	n/a		n/a	8 proprietary
Apple IIc	MOSTek	1 MHz /	none	none	1.4 MHz /	8-bit	none	none		none	none
Apple IIc Plus	MOSTek	1 MHz /	none	none	1.4 MHz /	8-bit	none	none		none	none
Apple IIe	MOS	1 MHz	none	none	1 MHz	8-bit	n/a	n/a		n/a	8 proprietary
Apple IIe (extended/enhanced)	MOS	1 MHz	none	none	1 MHz	8-bit	n/a	n/a		n/a	8 proprietary
Apple IIgs	Western	2.8 MHz	none	none	1 MHz	16-bit	none	none		none	7 proprietary
Apple III	Synertek	2 MHz	none	none	1 MHz	8-bit	n/a	n/a		n/a	4 proprietary
Apple III+	Synertek	2 MHz	none	none	1 MHz	8-bit	n/a	n/a		n/a	4 proprietary
DayStar Genesis LT 400+	604e	180 MHz	none	none	45 MHz		32K	512K		none	6 PCI
DayStar Genesis MP 300	604	150 MHz	none	none	50 MHz		32K	512K		none	6 PCI
DayStar Genesis MP 360+	604e	180 MHz	none	none	45 MHz		32K	512K		none	6 PCI
DayStar Genesis MP 400+	604e	180 MHz	none	none	45 MHz		32K	512K		none	6 PCI
DayStar Genesis MP 450+	604e	233 MHz	none	none	50 MHz		32K	512K		none	6 PCI
DayStar Genesis MP 466+	604e	233 MHz	none	none	50 MHz		32K	512K		none	6 PCI
DayStar Genesis MP 528	604	132 MHz	none	none	44 MHz		32K	512K		none	6 PCI
DayStar Genesis MP 600	604	132 MHz	none	none	44 MHz		32K	512K		none	6 PCI
DayStar Genesis MP 720+	604e	180 MHz	none	none	45 MHz		32K	512K		none	6 PCI
DayStar Genesis MP 800+	604e	180 MHz	none	none	45 MHz		32K	512K		none	6 PCI
DayStar Genesis MP 900+	604e	233 MHz	none	none	50 MHz		32K	512K		none	6 PCI
DayStar Genesis MP 932+	604e	233 MHz	none	none	50 MHz		32K	512K		none	6 PCI
eMac	G4	700 MHz	integrated	integrated	100 MHz	64-bit	32K	256K		none	
eMac (Late 2002)	G4	700 or	integrated	integrated	100 MHz	64-bit	32K	256K		none	
eMate 300	ARM 710	25 MHz	none	none			n/a	n/a		n/a	1 PCMCIA
iBook	G3	300 MHz	integrated	integrated	66/66	64-bit	64K	512K		none	
iBook 12.1" (2002)	G3	500 or	integrated	integrated	66 or 100	64-bit	64K	256K		none	0
iBook 12.1" (Late 2002)	G3	700 or	integrated	integrated	100 Mhz	64-bit	64K	256K		none	0
iBook 14.1" (2002)	G3	600 MHz	integrated	integrated	100 Mhz	64-bit	64K	256K		none	0
iBook 14.1" (Late 2002)	G3	800 MHz	integrated	integrated	100 Mhz	64-bit	64K	256K		none	0
iBook (Dual-USB)	G3	500 MHz	integrated	integrated	66 Mhz	64-bit	64K	256K		none	
iBook (Dual-USB/Late 2001)	G3	500 or	integrated	integrated	100 Mhz	64-bit	64K	256K		none	
iBook (Mid 2002)	G3	600 or	integrated	integrated	100 Mhz	64-bit	64K	512K		none	
iBook SE	G3	366 MHz	integrated	integrated	66/66	64-bit	64K	512K		none	
iBook/SE (FireWire)	G3	366 or	integrated	integrated	66/66	64-bit	64K	512K		none	
iMac (5 Flavors, 266 MHz) "Rev. C"	G3	266 MHz	integrated	integrated	66 MHz	64-bit	32K	512K		none	0
iMac (5 Flavors, 333 MHz) "Rev. D"	G3	333 MHz	integrated	integrated	100 MHz	64-bit	32K	512K		none	0
iMac (500 MHz - Late 2001)	G3	500 MHz	integrated	integrated	100 MHz	64-bit	32K	256K		none	0
iMac (600 MHz - Late 2001)	G3	600 MHz	integrated	integrated	100 MHz	64-bit	32K	256K		none	0
iMac (Bondi Blue, 233 MHz)	G3	233 MHz	integrated	integrated	66 MHz	64-bit	32K	512K		none	mezzanine
iMac DV SE (Summer 2000)	G3	500 MHz	integrated	integrated	100 MHz	64-bit	32K	512K		none	0
iMac DV (Summer 2000)	G3	400 MHz	integrated	integrated	100 MHz	64-bit	32K	512K		none	0
iMac DV+ (Summer 2000)	G3	450 MHz	integrated	integrated	100 MHz	64-bit	32K	512K		none	0
iMac DV/SE	G3	350 or	integrated	integrated	100 MHz	64-bit	32K	512K		none	0
iMac (Early 2001)	G3	400/500	integrated	integrated	100 MHz	64-bit	32K	256K		none	0
iMac "Luxo" (700 MHz - LCD)	G4	700 MHz	integrated	integrated	100 MHz	64-bit	32K	256K		none	0
iMac "Luxo" (700 MHz - LCD - Summer 2002)	G4	700 MHz	integrated	integrated	100 MHz	64-bit	32K	256K		none	0
iMac "Luxo" (800 MHz - LCD)	G4	800 MHz	integrated	integrated	100 MHz	64-bit	32K	256K		none	0
iMac "Luxo" (800 MHz - LCD - Summer 2002)	G4	800 MHz	integrated	integrated	100 MHz	64-bit	32K	256K		none	0
iMac "Luxo" Widescreen (800 MHz - LCD)	G4	800 MHz	integrated	integrated	100 MHz	64-bit	32K	256K		none	0
iMac SE (Early 2001)	G3	600 MHz	integrated	integrated	100 MHz	64-bit	32K	256K		none	0
iMac Special Edition (700 MHz - Late 2001)	G3	700 MHz	integrated	integrated	100 MHz	64-bit	32K	256K		none	0
iMac/iMac DV (Slot Loading CD-ROM)	G3	350 or	integrated	integrated	100 MHz	64-bit	32K	512K		none	0
Interactive Television Box											
Lisa/Lisa2	68000	5 MHz	none	none	5 MHz	16-bit	none	none		none	2 Lisa slots
Macintosh 128K	68000	8 MHz	none	none	8 MHz	16-bit	none	none		none	none
Macintosh 512K	68000	8 MHz	none	none	8 MHz	16-bit	none	none		none	none
Macintosh 512Ke	68000	8 MHz	none	none	8 MHz	16-bit	none	none		none	none
Macintosh Centris 610	68LC040	20 MHz	integrated	none	20 MHz	32-bit	8K	none		none	1 7" NuBus or PDS
Macintosh Centris 650	68040	25 MHz	integrated	optional	25 MHz	32-bit	8K	none		none	3 NuBus, 1 PDS
Macintosh Centris 660AV	68040	25MHz	integrated	integrated	25 MHz	32-bit	8K	none		AT&T 3210 DSP, 55 MHz	one 7" NuBus or PDS
Macintosh Classic	68000	8 MHz	none	none	8 MHz	16-bit	none	none		none	none
Macintosh Classic II	68030	16 MHz	integrated	none	16 MHz	16-bit	0.5K	none		none	none
Macintosh Color Classic	68030	16 MHz	integrated	opt. 68882	16 MHz	16-bit	0.5K	none		none	1 LC PDS
Macintosh Color Classic II	68030	33 MHz	integrated	opt. 68882	33 MHz	32-bit	0.5K	none		none	1 LC PDS
Macintosh Duo Dock	none	n/a	n/a	opt. 68882	n/a	n/a	n/a	none		n/a	2 NuBus
Macintosh Duo Dock II	none	n/a	n/a	opt. 68882	n/a	n/a	n/a	none		n/a	2 NuBus
Macintosh Duo Dock Plus	none	n/a	n/a	opt. 68882	n/a	n/a	n/a	none		n/a	2 NuBus
Macintosh Duo MiniDock	none	n/a	n/a	none	n/a	n/a	n/a	none		n/a	none
Macintosh II	68020	16 MHz	opt. 68851	68881	16 MHz	32-bit	0.25K	none		none	6 NuBus
Macintosh IIci	68030	25 MHz	integrated	68882	25 MHz	32-bit	0.5K	32K		none	3 NuBus, 1 cache
Macintosh IIcx	68030	16 MHz	integrated	68882	16 MHz	32-bit	0.5K	none		none	3 NuBus
Macintosh IIfx	68030	40 MHz	integrated	68882	40 MHz	32-bit	0.5K	32K		none	6 NuBus, 1 PDS
Macintosh IIsi	68030	20 MHz	integrated	opt. 68882	20 MHz	32-bit	0.5K	none		none	1 NuBus or PDS
Macintosh IIvi	68030	16 MHz	integrated	opt. 68882	16 MHz	32-bit	0.5K	none		none	3 NuBus, 1 PDS
Macintosh IIvx	68030	32 MHz	integrated	68882	16 MHz	32-bit	0.5K	32K		none	3 NuBus, 1 PDS
Macintosh IIfx	68030	16 MHz	integrated	68882	16 MHz	32-bit	0.5K	none		none	6 NuBus
Macintosh LC	68020	16 MHz	none	none	16 MHz	16-bit	0.25K	none		none	1 LC PDS

Logic Board

Name	Processor	Speed	PMMU	FPU	Data Path Speed	Data Path Size	Caches L1	L2	L3	Secondary Processor	Slots
Macintosh Performa 6410	603e	180 MHz	integrated	integrated	40 MHz	64-bit	32K	opt.		opt. PC Compatibility Card	2 PCI, Comm II, TV, video in
Macintosh Performa 6420	603e	200 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		opt. PC Compatibility Card	2 PCI, Comm II, TV, video in
Macintosh Plus	68000	8 MHz	none	none	8 MHz	16-bit	none	none		none	none
Macintosh Portable	68000	16 MHz	none	none	16 MHz	16-bit	none	none		none	modem
Macintosh PowerBook 100	68000	16 MHz	none	none	16 MHz	16-bit	none	none		none	modem
Macintosh PowerBook 140	68030	16 MHz	integrated	none	16 MHz	32-bit	0.5K	none		none	modem
Macintosh PowerBook 1400c/117	603e	117 MHz	integrated	integrated	33.3 MHz	64-bit	32K	none		none	2 Type II PC Card (1 Type
Macintosh PowerBook 1400c/133	603e	133 MHz	integrated	integrated	33.3 MHz	64-bit	32K	128K		none	2 Type II PC Card (1 Type
Macintosh PowerBook 1400c/166	603e	166 MHz	integrated	integrated	33.3 MHz	64-bit	32K	128K		none	2 Type II PC Card (1 Type
Macintosh PowerBook 1400cs/117	603e	117 MHz	integrated	integrated	33.3 MHz	64-bit	32K	none		none	2 Type II PC Card (1 Type
Macintosh PowerBook 1400cs/133	603e	133 MHz	integrated	integrated	33.3 MHz	64-bit	32K	128K		none	2 Type II PC Card (1 Type
Macintosh PowerBook 1400cs/166	603e	166MHz	integrated	integrated	33.3MHz	64-bit	32K	128K		none	2 Type II PC Card (1 Type
Macintosh PowerBook 145	68030	25 MHz	integrated	none	25 MHz	32-bit	0.5K	none		none	modem
Macintosh PowerBook 145B	68030	25 MHz	integrated	none	25 MHz	32-bit	0.5K	none		none	modem
Macintosh PowerBook 150	68030	33 MHz	integrated	none	33 MHz	32-bit	0.5K	none		none	modem
Macintosh PowerBook 160	68030	25 MHz	integrated	none	25 MHz	32-bit	0.5K	none		none	modem
Macintosh PowerBook 165	68030	33 MHz	integrated	none	33 MHz	32-bit	0.5K	none		none	modem
Macintosh PowerBook 165c	68030	33 MHz	integrated	68882	33 MHz	32-bit	0.5K	none		none	modem
Macintosh PowerBook 170	68030	25 MHz	integrated	68882	25 MHz	32-bit	0.5K	none		none	modem
Macintosh PowerBook 180	68030	33 MHz	integrated	68882	33 MHz	32-bit	0.5K	none		none	modem
Macintosh PowerBook 180c	68030	33 MHz	integrated	68882	33 MHz	32-bit	0.5K	none		none	modem
Macintosh PowerBook 190/66	68LC040	66 MHz	integrated	none	33 MHz	32-bit	8K	none		none	2 Type II PC Card (1 Type
Macintosh PowerBook 190cs/66	68LC040	66 MHz	integrated	none	33 MHz	32-bit	8K	none		none	2 Type II PC Card (1 Type
Macintosh PowerBook 2400c/180	603e	180 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		none	2 Type II PC Card (1 Type
Macintosh PowerBook 2400c/240	603e	240 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		none	2 Type II PC Card (1 Type
Macintosh PowerBook 3400c/180	603e	180 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		none	2 Type II PC Card (1 Type
Macintosh PowerBook 3400c/200	603e	200 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		none	2 Type II PC Card (1 Type
Macintosh PowerBook 3400c/240	603e	240 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		none	2 Type II PC Card (1 Type
Macintosh PowerBook 500 with PowerPC	603e	100 MHz	integrated	integrated	33 MHz	64-bit	32K	none		none	modem
Macintosh PowerBook 520	68LC040	50 MHz	integrated	none	25 MHz	32-bit	8K	none		none	modem
Macintosh PowerBook 520c	68LC040	50 MHz	integrated	none	25 MHz	32-bit	8K	none		none	modem
Macintosh PowerBook 5300/100	603e	100 MHz	integrated	integrated	33.3 MHz	64-bit	32K	none		none	2 Type II PC Card (1 Type
Macintosh PowerBook 5300c/100	603e	100 MHz	integrated	integrated	33.3 MHz	64-bit	32K	none		none	2 Type II PC Card (1 Type
Macintosh PowerBook 5300ce/117	603e	117 MHz	integrated	integrated	33.3 MHz	64-bit	32K	none		none	2 Type II PC Card (1 Type
Macintosh PowerBook 5300cs/100	603e	100 MHz	integrated	integrated	33.3 MHz	64-bit	32K	none		none	2 Type II PC Card (1 Type
Macintosh PowerBook 540	68LC040	66 MHz	integrated	none	33 MHz	32-bit	8K	none		none	modem
Macintosh PowerBook 540c	68LC040	66 MHz	integrated	none	33 MHz	32-bit	8K	none		none	modem
Macintosh PowerBook 550c	68040	66 MHz	integrated	none	33 MHz	32-bit	8K	none		none	modem
Macintosh PowerBook Duo 210	68030	25 MHz	integrated	opt. in	25 MHz	32-bit	0.5K	none		none	modem, dock
Macintosh PowerBook Duo 230	68030	33 MHz	integrated	opt. in	33 MHz	32-bit	0.5K	none		none	modem, dock
Macintosh PowerBook Duo 2300c/100	603e	100 MHz	integrated	integrated	33 MHz	64-bit	32K	none		none	modem, dock
Macintosh PowerBook Duo 250	68030	33 MHz	integrated	opt. in	33 MHz	32-bit	0.5K	none		none	modem, dock
Macintosh PowerBook Duo 270c	68030	33 MHz	integrated	68882	33 MHz	32-bit	0.5K	none		none	modem, dock
Macintosh PowerBook Duo 280	68LC040	66 MHz	integrated	none	33 MHz	32-bit	8K	none		none	modem, dock
Macintosh PowerBook Duo 280c	68LC040	66 MHz	integrated	none	33 MHz	32-bit	8K	none		none	modem, dock
Macintosh PowerBook G3	G3	250MHz	integrated	integrated	50Mhz	64-bit	n/a	512K		none	2 Type II PC Card (1 Type
Macintosh Quadra 605	68LC040	25 MHz	integrated	none	25 MHz	32-bit	8K	none		none	1 LC III PDS
Macintosh Quadra 610	68040	25 MHz	integrated	optional	25 MHz	32-bit	8K	none		opt. Intel 486SX-25	one 7" NuBus or PDS
Macintosh Quadra 610 DOS Compatible	68040	25 MHz	integrated	optional	25 MHz	32-bit	8K	none		Intel 486SX-25	PDS filled
Macintosh Quadra 630	68040	33 MHz	integrated	integrated	33 MHz	32-bit	8K	none		none	LC, comm, TV, video in
Macintosh Quadra 650	68040	33 MHz	integrated	integrated	33 MHz	32-bit	8K	none		none	3 NuBus, 1 PDS
Macintosh Quadra 660AV	68040	25 MHz	integrated	integrated	25 MHz	32-bit	8K	none		AT&T 3210 DSP, 55 MHz	one 7" NuBus or PDS
Macintosh Quadra 700	68040	25 MHz	integrated	integrated	25 MHz	32-bit	8K	none		none	2 NuBus, 1 PDS
Macintosh Quadra 800	68040	33 MHz	integrated	integrated	33 MHz	32-bit	8K	none		none	3 NuBus, 1 PDS
Macintosh Quadra 840AV	68040	40 MHz	integrated	integrated	40 MHz	32-bit	8K	none		AT&T 3210 DSP, 66.67 MHz	3 NuBus
Macintosh Quadra 900	68040	25 MHz	integrated	integrated	25 MHz	32-bit	8K	none		none	5 NuBus, 1 PDS
Macintosh Quadra 950	68040	66 MHz	integrated	integrated	33 MHz	32-bit	8K	none		none	5 NuBus, 1 PDS
Macintosh SE	68000	8 MHz	none	none	8 MHz	16-bit	none	none		none	1 SE PDS
Macintosh SE FDHD	68000	8 MHz	none	none	8 MHz	16-bit	none	none		none	1 SE PDS
Macintosh SE/30	68030	16 MHz	integrated	68882	16 MHz	32-bit	0.5K	none		none	1 SE/30 PDS
Macintosh Server G3	G3	233/266*		integrated	32K	64-bit		512K			3 PCIs,
Macintosh Server G4 with AppleShare IP	G4	450 or	integrated	integrated	100 MHz	128-bit	32K	1 MB			3 PCI , one AGP
Macintosh Server G4 with Mac OS X Server	G4	500 MHz	integrated	integrated	100 MHz	128-bit	32K	1 MB			3 PCI , one AGP
Macintosh TV	68030	32 MHz	integrated	none	16 MHz	32-bit	0.5K	none		none	none
Macintosh XL	68000	5 MHz	none	none	5 MHz	16-bit	none	none		none	3 Lisa slots
Motorola StarMax 3000/160	603e	160 MHz	none	none	40 MHz		32K	256-51		none	PCI: 3 on Desktop, 5 on
Motorola StarMax 3000/180	603e	180 MHz	none	none	40 MHz		32K	256-51		none	PCI: 3 on Desktop, 5 on
Motorola StarMax 3000/200	603e	200 MHz	none	none	40 MHz		32K	256-51		none	PCI: 3 on Desktop, 5 on
Motorola StarMax 3000/240	603e	240 MHz	none	none	40 MHz		32K	256-51		none	PCI: 3 on Desktop, 5 on
Motorola StarMax 4000/160	604e	160 MHz	none	none	40 MHz		32K	512K		none	PCI: 3 on Desktop, 5 on
Motorola StarMax 4000/200	604e	200 MHz	none	none	40 MHz		32K	512K		none	PCI: 3 on Desktop, 5 on
Motorola StarMax 5000/225	603e	200 MHz	none	none	50 MHz		32K	512K		none	5 PCI
Motorola StarMax 5000/250	603e	250 MHz	none	none	50 MHz		32K	512K		none	5 PCI
Motorola StarMax 5000/275	603e	275 MHz	none	none	50 MHz		32K	512K		none	5 PCI
Motorola StarMax 5000/300	603e	300 MHz	none	none	50 MHz		32K	512K		none	5 PCI
Motorola StarMax 5500/200	604e	200 MHz	none	none	50 MHz		32K	512K		none	5 PCI
Network Server 500/132	604	132 MHz	integrated	integrated	44 MHz	64-bit	32K	512K		none	6 PCI
Network Server 700/150	604	150 MHz	integrated	integrated	50 MHz	64-bit	32K	1MB		none	6 PCI
Network Server 700/200	604e	200 MHz	integrated	integrated	50 MHz	64-bit	64K	1MB		none	6 PCI

Logic Board

Name	Processor	Speed	PMMU	FPU	Data Path Speed	Data Path Size	Caches			Secondary Processor	Slots
							L1	L2	L3		
Newton MessagePad 100	ARM 610	20 MHz	none	none			none	none		n/a	1 PCMCIA
Newton MessagePad 110	ARM 610	20 MHz	none	none			none	none		n/a	1 PCMCIA
Newton MessagePad 120a	ARM 610	20 MHz	none	none			none	none		n/a	1 PCMCIA
Newton MessagePad 120b	ARM 610	20 MHz	none	none			none	none		n/a	1 PCMCIA
Newton MessagePad 130	ARM 610	20 Mhz	none	none			none	none		n/a	1 PCMCIA
Newton MessagePad 2000	StrongAR	162 MHz	none	none			none	none		n/a	2 PCMCIA
Newton MessagePad 2100	StrongAR	162 MHz	none	none			none	none		n/a	2 PCMCIA
Newton MessagePad (Original MessagePad	ARM 610	20 MHz	none	none			none	none		n/a	1 PCMCIA
NeXT Cube	68030	25 MHz	integrated	25 MHz							
NeXTcube	68040	25 MHz	integrated	25 MHz							
NeXTdimension	68040	25 MHz	integrated	25 MHz							
NeXTstation	68040	25 MHz	integrated								
NeXTstation Color	68040	25 MHz	integrated								
Pippin	603	66 MHz									1 PCI
Power Computing Power 100 Desktop	601	100 MHz	none	non	33 MHz		32K	256-51		none	3 NuBus, 1 PDS
Power Computing Power 100 Tower	601	100 MHz	none	non	33 MHz		32K	256-51		none	3 NuBus, 1 PDS
Power Computing Power 120 Desktop	601	120 MHz	none	non	40 MHz		32K	256-51		none	3 NuBus, 1 PDS
Power Computing Power 120 Tower	601	120 MHz	none	non	40 MHz		32K	256-51		none	3 NuBus, 1 PDS
Power Computing Power 80 Desktop	601	80 MHz	none	non	33 MHz		32K	256-51		none	3 NuBus, 1 PDS
Power Computing Power 80 Tower	601	80 MHz	none	non	33 MHz		32K	256-51		none	3 NuBus, 1 PDS
Power Computing PowerBase 180 Low	603e	180 MHz	none	none	40 MHz		32K	256K		none	3 PCI
Power Computing PowerBase 180 Tower	603e	180 MHz	none	none	40 MHz		32K	256K		none	3 PCI
Power Computing PowerBase 200 Low	603e	200 MHz	none	none	40 MHz		32K	256K		none	3 PCI
Power Computing PowerBase 200 Tower	603e	200 MHz	none	none	40 MHz		32K	256K		none	3 PCI
Power Computing PowerBase 240 Low	603e	240 MHz	none	none	40 MHz		32K	256K		none	3 PCI
Power Computing PowerBase 240 Tower	603e	240 MHz	none	none	40 MHz		32K	256K		none	3 PCI
Power Computing PowerCenter 120 Desktop	604	120 MHz	none	none	40 MHz		32K	512K		none	3 PCI
Power Computing PowerCenter 120 Low	604	120 MHz	none	none	40 MHz		32K	512K		none	3 PCI
Power Computing PowerCenter 120 Tower	604	120 MHz	none	none	40 MHz		32K	512K		none	3 PCI
Power Computing PowerCenter 132 Desktop	604	132 MHz	none	none	44 MHz		32K	512K		none	3 PCI
Power Computing PowerCenter 132 Low	604	132 MHz	none	none	44 MHz		32K	512K		none	3 PCI
Power Computing PowerCenter 132 Tower	604	132 MHz	none	none	44 MHz		32K	512K		none	3 PCI
Power Computing PowerCenter 140 Low	604	150 MHz	none	none	50 MHz		32K	512K		none	3 PCI
Power Computing PowerCenter 140 Tower	604	150 MHz	none	none	50 MHz		32K	512K		none	3 PCI
Power Computing PowerCenter 150 Desktop	604	150 MHz	none	none	50 MHz		32K	512K		none	3 PCI
Power Computing PowerCenter 166 Desktop	604	166 MHz	none	none	55.3 MHz		32K	512K		none	3 PCI
Power Computing PowerCenter 166 Low	604	166 MHz	none	none	55.3 MHz		32K	512K		none	3 PCI
Power Computing PowerCenter 166 Tower	604	166	none	none	55.3 MHz		32K	512K		none	3 PCI
Power Computing PowerCenter 180 Desktop	604	180 MHz	none	none	60 MHz		32K	512K		none	3 PCI
Power Computing PowerCenter 180 Low	604	180 MHz	none	none	60 MHz		32K	512K		none	3 PCI
Power Computing PowerCenter 180 Tower	604	180 MHz	none	none	60 MHz		32K	512K		none	3 PCI
Power Computing PowerCenter 210 Desktop	604e	210 MHz	none	none	60 MHz		32K	512K		none	3 PCI
Power Computing PowerCenter 210 Low	604e	210 MHz	none	none	60 MHz		32K	512K		none	3 PCI
Power Computing PowerCenter 210 Tower	604e	210 MHz	none	none	60 MHz		32K	512K		none	3 PCI
Power Computing PowerCenter Pro 180	604e	180 MHz	none	none	60 MHz		32K	1MB		none	3 PCI
Power Computing PowerCenter Pro 180	604e	180 MHz	none	none	60 MHz		32K	1MB		none	3 PCI
Power Computing PowerCenter Pro 210	604e	210 MHz	none	none	60 MHz		32K	1MB		none	3 PCI
Power Computing PowerCenter Pro 210	604e	210 MHz	none	none	60 MHz		32K	1MB		none	3 PCI
Power Computing PowerCenter Pro 240	604e	240 MHz	none	none	60 MHz		32K	1MB		none	3 PCI
Power Computing PowerCenter Pro 240	604e	240 MHz	none	none	60 MHz		32K	1MB		none	3 PCI
Power Computing PowerCurve 120	601	120 MHz	none	non	40 MHz		32K	256K-1		none	3 PCI
Power Computing PowerTower 166	604	166	none	none	55.3 MHz		32K	512K		none	3 PCI
Power Computing PowerTower 180	604	180 MHz	none	none	60 MHz		32K	512K		none	3 PCI
Power Computing PowerTower 200	604e	200 MHz	none	none	60 MHz		32K	512K		none	3 PCI
Power Computing PowerTower Pro 180	604e	180 MHz	none	none	40 MHz		32K	1MB		none	6 PCI
Power Computing PowerTower Pro 200	604e	200 MHz	none	none	40 MHz		32K	1MB		none	6 PCI
Power Computing PowerTower Pro 225	604e	225 MHz	none	none	51.4 MHz		32K	1MB		none	6 PCI
Power Computing PowerTower Pro 250	604e	250 MHz	none	none	51.4 MHz		32K	1MB		none	6 PCI
Power Computing PowerWave 120 Desktop	604	120 MHz	none	none	40 MHz		32K	256K-1		none	3 PCI
Power Computing PowerWave 120 Tower	604	120 MHz	none	none	40 MHz		32K	256K-1		none	3 PCI
Power Computing PowerWave 132 Desktop	604	132 MHz	none	none	44 MHz		32K	256K-1		none	3 PCI
Power Computing PowerWave 132 Tower	604	132 MHz	none	none	44 MHz		32K	256K-1		none	3 PCI
Power Computing PowerWave 150 Desktop	604	150 MHz	none	none	50 MHz		32K	256K-1		none	3 PCI
Power Computing PowerWave 150 Tower	604	150 MHz	none	none	50 MHz		32K	256K-1		none	3 PCI
Power Mac G4 - AGP Graphics	G4	350, 400,	integrated	integrated	100 MHz	64-bit	64K	1 MB		none	4 PCI , one dedicated to
Power Mac G4 Cube	G4	450, 500	integrated	integrated	100 MHz	64-bit	32k/32	1 MB		none	1 AGP
Power Mac G4 (Digital Audio)	G4	466/533/	integrated	integrated	133 MHz	64-bit	32K	1 MB		Second G4 on 533 optional	4 PCI , one AGP
Power Mac G4 (Gigabit Ethernet)	G4	400,	integrated	integrated	100 MHz	64-bit	32k/32	1 MB		Second G4 on 450 and 500	3 PCI , one AGP
Power Mac G4 (Mirrored Drive Doors - Late	G4	867	integrated	integrated	167 MHz	128-bit	32K	256 K	2 MB	Second G4 on 867 MHz, 1	4PCI , 1 AGP
Power Mac G4 - PCI Graphics	G4	350,	integrated	integrated	100 MHz	64-bit	64K	512K/1		none	4 PCI, one dedicated to
Power Mac G4 (Quick Silver)	G4	733/800/	integrated	integrated	133 MHz	64-bit	32K	256 K	2 MB	Second G4 on 800	4PCI , 1 AGP
Power Mac G4 (Quick Silver - Early 2002)	G4	800/933/	integrated	integrated	133 MHz	128-bit	32K	256 K	2 MB	Second G4 on 1000	4PCI , 1 AGP
Power Macintosh 4400/160	603e	160 MHz	integrated	integrated	40 MHz	64-bit	32K	opt'l.		none	3 PCI
Power Macintosh 4400/200	603e	200 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		none	2 PCI, comm II
Power Macintosh 4400/200 PC Compatible	603e	200 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		Cyrix P166 6x86	2 PCI, comm II
Power Macintosh 475/605	601	50 MHz	integrated	integrated	25 MHz	64-bit	32K	256K		68LC040, 50 MHz	LC PDS (unavailable)
Power Macintosh 5200/75 LC	603	75 MHz	integrated	integrated	37.5 MHz	64-bit	16K	256K		none	LC, comm, TV, video in/out
Power Macintosh 5260/100	603e	100 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		none	LC, comm, TV, video in/out
Power Macintosh 5260/120	603e	120 MHz	integrated	integrated	40 MHz	64-bit	32K	opt'l.		none	LC, comm, TV, video in/out

Logic Board

Name	Processor	Speed	PMMU	FPU	Data Path Speed	Data Path Size	Caches			Secondary Processor	Slots
							L1	L2	L3		
Power Macintosh 5300/100 LC	603e	100 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		none	LC, comm, TV, video in/out
Power Macintosh 5400/120	603e	120 MHz	integrated	integrated	40 MHz	64-bit	32K	opt'l.		opt. PC Compatibility Card	PCI, comm, TV, video in/out
Power Macintosh 5400/180	603e	180 MHz	integrated	integrated	40 MHz	64-bit	32K	opt'l.		opt. PC Compatibility Card	PCI, comm, TV, video in/out
Power Macintosh 5400/200	603e	200 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		opt. PC Compatibility Card	PCI, comm, TV, video in/out
Power Macintosh 5500/225	603e	225 MHz	integrated	integrated	50 MHz	64-bit	32K	256K		none	PCI, comm, TV, video in/out
Power Macintosh 5500/250	603e	250 MHz	integrated	integrated	50 MHz	64-bit	32K	256K		none	PCI, comm, TV, video in/out
Power Macintosh 575	601	66 MHz	integrated	integrated	33 MHz	64-bit	32K	256K		68LC040, 66 MHz	LC (unavail.), comm
Power Macintosh 580	601	66 MHz	integrated	integrated	33 MHz	64-bit	32K	256K		68LC040, 66 MHz	Comm, video in/out
Power Macintosh 6100/60	601	60 MHz	integrated	integrated	30 MHz	64-bit	32K	opt'l.		opt. Intel 486DX2-66	one 7" NuBus or PDS
Power Macintosh 6100/60AV	601	60 MHz	integrated	integrated	30 MHz	64-bit	32K	opt'l.		none	PDS filled
Power Macintosh 6100/66	601	66 MHz	integrated	integrated	33 MHz	64-bit	32K	256K		opt. Intel 486DX2-66	one 7" NuBus or PDS
Power Macintosh 6100/66 DOS Compatible	601	66 MHz	integrated	integrated	33 MHz	64-bit	32K	256K		Intel 486DX2-66	PDS filled
Power Macintosh 6100/66AV	601	66 MHz	integrated	integrated	33 MHz	64-bit	32K	256K		none	PDS filled
Power Macintosh 6200/75	603	75 MHz	integrated	integrated	37.5 MHz	64-bit	16K	256K		none	LC, comm, TV, video in/out
Power Macintosh 630	601	66 MHz	integrated	integrated	33 MHz	64-bit	32K	256K		68LC040/68040, 66 MHz	Comm, TV, video in
Power Macintosh 6300/120	603e	120 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		none	LC, comm, TV, video in/out
Power Macintosh 6300/160	603e	160 MHz	integrated	integrated	40 MHz	64-bit	32K	opt'l.		opt. PC Compatibility Card	PCI, comm, TV, video in/out
Power Macintosh 6400/180	603e	180 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		opt. PC Compatibility Card	2 PCI, Comm II, TV, video in
Power Macintosh 6400/200	603e	200 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		opt. PC Compatibility Card	2 PCI, Comm II, TV, video in
Power Macintosh 6500/225	603e	225 MHz	integrated	integrated	50 MHz	64-bit	32K	256K		none	2 PCI, Comm II, TV, video in
Power Macintosh 6500/250	603e	250 MHz	integrated	integrated	50 MHz	64-bit	32K	256K		none	2 PCI, Comm II, TV, video in
Power Macintosh 6500/275	603e	275 MHz	integrated	integrated	50 MHz	64-bit	32K	512K		none	2 PCI, Comm II, TV, video in
Power Macintosh 6500/300	603e	300 MHz	integrated	integrated	50 MHz	64-bit	32K	512K		none	2 PCI, Comm II, TV, video in
Power Macintosh 700	601	50 MHz	integrated	integrated	25 MHz	64-bit	32K	1MB		68040, 50/25 MHz	2 NuBus, PDS filled
Power Macintosh 7100/66	601	66 MHz	integrated	integrated	33 MHz	64-bit	32K	opt'l.		none	3 NuBus, PDS filled
Power Macintosh 7100/66AV	601	66 MHz	integrated	integrated	33 MHz	64-bit	32K	opt'l.		none	3 NuBus, PDS filled
Power Macintosh 7100/80	601	80 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		none	3 NuBus, PDS filled
Power Macintosh 7100/80AV	601	80 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		none	3 NuBus, PDS filled
Power Macintosh 7200/120	601	120 MHz	integrated	integrated	40 MHz	64-bit	32K	opt'l.		opt. PC Compatibility Card	3 PCI
Power Macintosh 7200/120 PC Compatible	601	120 MHz	integrated	integrated	40 MHz	64-bit	32K	opt'l.		100 MHz Pentium or 586	3 PCI
Power Macintosh 7200/75	601	75 MHz	integrated	integrated	37.5 MHz	64-bit	32K	opt'l.		opt. PC Compatibility Card	3 PCI
Power Macintosh 7200/90	601	90 MHz	integrated	integrated	45 MHz	64-bit	32K	opt'l.		opt. PC Compatibility Card	3 PCI
Power Macintosh 7215/90	601	90 MHz	integrated	integrated	45 MHz	64-bit	32K	opt'l.		opt. PC Compatibility Card	3 PCI
Power Macintosh 7220/200	603e	200 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		none	2 PCI, comm II
Power Macintosh 7220/200 PC Compatible	603e	200 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		Cyrix P166 6x86	2 PCI, comm II
Power Macintosh 7300/166	604e	166 MHz	integrated	integrated	50 MHz	64-bit	64K	256K		opt. PC Compatibility Card	3 PCI
Power Macintosh 7300/180	604e	180 MHz	integrated	integrated	45 MHz	64-bit	64K	256K		opt. PC Compatibility Card	3 PCI
Power Macintosh 7300/180 PC Compatible	604e	180 MHz	integrated	integrated	45 MHz	64-bit	64K	256K		166 MHz Pentium	3 PCI
Power Macintosh 7300/200	604e	200 MHz	integrated	integrated	50 MHz	64-bit	64K	256K		opt. PC Compatibility Card	3 PCI
Power Macintosh 7500/100	601	100 MHz	integrated	integrated	50 MHz	64-bit	32K	opt'l.		opt. PC Compatibility Card	3 PCI
Power Macintosh 7600/120	604	120 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		opt. PC Compatibility Card	3 PCI
Power Macintosh 7600/132	604	132 MHz	integrated	integrated	44 MHz	64-bit	32K	256K		opt. PC Compatibility Card	3 PCI
Power Macintosh 7600/200	604e	200 MHz	integrated	integrated	50 MHz	64-bit	64K	256K		opt. PC Compatibility Card	3 PCI
Power Macintosh 800	601	66 MHz	integrated	integrated	33 MHz	64-bit	32K	1MB		68040, 66/33 MHz	3 NuBus, PDS filled
Power Macintosh 8100/100	601	100 MHz	integrated	integrated	33.3 MHz	64-bit	32K	256K		none	3 NuBus, PDS filled
Power Macintosh 8100/100AV	601	100 MHz	integrated	integrated	33.3 MHz	64-bit	32K	256K		none	3 NuBus, PDS filled
Power Macintosh 8100/110	601+	110 MHz	integrated	integrated	36.7 MHz	64-bit	32K	256K		none	3 NuBus, PDS filled
Power Macintosh 8100/80	601	80 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		none	3 NuBus, PDS filled
Power Macintosh 8100/80AV	601	80 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		none	3 NuBus, PDS filled
Power Macintosh 8115/110	601+	110 MHz	integrated	integrated	36.7 MHz	64-bit	32K	256K		none	3 NuBus, PDS filled
Power Macintosh 8200/100	601	100 MHz	integrated	integrated	40 MHz	64-bit	32K	opt'l.		opt. PC Compatibility Card	3 PCI
Power Macintosh 8200/120	601	120 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		opt. PC Compatibility Card	3 PCI
Power Macintosh 8500/120	604	120 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		opt. PC Compatibility Card	3 PCI
Power Macintosh 8500/132	604	132 MHz	integrated	integrated	44 MHz	64-bit	32K	256K		opt. PC Compatibility Card	3 PCI
Power Macintosh 8500/150	604	150 MHz	integrated	integrated	50 MHz	64-bit	32K	256K		opt. PC Compatibility Card	3 PCI
Power Macintosh 8500/180	604e	180 MHz	integrated	integrated	45 MHz	64-bit	64K	256K		opt. PC Compatibility Card	3 PCI
Power Macintosh 8515/120	604	120 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		opt. PC Compatibility Card	3 PCI
Power Macintosh 8600/200	604e	200 MHz	integrated	integrated	50 MHz	64-bit	64K	256K		opt. PC Compatibility Card	3 PCI
Power Macintosh 8600/250	604e	250 MHz	integrated	integrated	100 MHz	64-bit	64K	1MB		opt. PC Compatibility Card	3 PCI
Power Macintosh 8600/300	604e	300 MHz	integrated	integrated	100 MHz	64-bit	64K	1MB		opt. PC Compatibility Card	3 PCI
Power Macintosh 900	601	50 MHz	integrated	integrated	25 MHz	64-bit	32K	1MB		68040, 50/25 MHz	5 NuBus, PDS filled
Power Macintosh 950	601	66 MHz	integrated	integrated	33 MHz	64-bit	32K	1MB		68040, 66/33 MHz	5 NuBus, PDS filled
Power Macintosh 9500/120	604	120 MHz	integrated	integrated	40 MHz	64-bit	32K	512K		opt. PC Compatibility Card	6 PCI
Power Macintosh 9500/132	604	132 MHz	integrated	integrated	44 MHz	64-bit	32K	512K		opt. PC Compatibility Card	6 PCI
Power Macintosh 9500/150	604	150 MHz	integrated	integrated	50 MHz	64-bit	32K	512K		opt. PC Compatibility Card	6 PCI
Power Macintosh 9500/180MP	two 604e	180 MHz	integrated	integrated	45 MHz	64-bit	64K	512K		opt. PC Compatibility Card	6 PCI
Power Macintosh 9500/200	604e	200 MHz	integrated	integrated	50 MHz	64-bit	64K	512K		opt. PC Compatibility Card	6 PCI
Power Macintosh 9515/132	604	132 MHz	integrated	integrated	44 MHz	64-bit	32K	512K		opt. PC Compatibility Card	6 PCI
Power Macintosh 9600/200	604e	200 MHz	integrated	integrated	50 MHz	64-bit	64K	512K		opt. PC Compatibility Card	6 PCI
Power Macintosh 9600/200MP	two 604e	200 MHz	integrated	integrated	50 MHz	64-bit	64K	512K		opt. PC Compatibility Card	6 PCI
Power Macintosh 9600/233	604e	233 MHz	integrated	integrated	50 MHz	64-bit	64K	512K		opt. PC Compatibility Card	6 PCI
Power Macintosh 9600/300	604e	300 MHz	integrated	integrated	100 MHz	64-bit	64K	1MB		opt. PC Compatibility Card	6 PCI
Power Macintosh 9600/350	604e	350 MHz	integrated	integrated	100 MHz	64-bit	64K	1MB		opt. PC Compatibility Card	6 PCI
Power Macintosh C610	601	40 MHz	integrated	integrated	20 MHz	64-bit	32K	1MB		68040, 40/20 MHz	PDS filled
Power Macintosh C650	601	50 MHz	integrated	integrated	25 MHz	64-bit	32K	1MB		68040, 50/25 MHz	3 NuBus, PDS filled
Power Macintosh G3 All-In-One	G3	233/266	integrated	integrated	66Mhz	64-bit	32K	512K		none	3 PCI
Power Macintosh G3 (Blue and White)	G3	350, 400,		integrated	100 MHz	64-bit	64K	512K/1		none	4 PCI, one dedicated to
Power Macintosh G3 Desktop	G3	266MHz*	integrated	integrated	66Mhz	64-bit	32K	512K		none	3 PCI, 1 Comm
Power Macintosh G3 Mini Tower	G3	266MHz*	integrated	integrated	66Mhz	64-bit	32K	512K		none	3 PCIs, 1 Comm

Logic Board

Name	Processor	Speed	PMU	FPU	Data Path Speed	Data Path Size	Caches			Secondary Processor	Slots
							L1	L2	L3		
Power Macintosh Q610	601	50 MHz	integrated	integrated	25 MHz	64-bit	32K	1MB		68040, 50/25 MHz	PDS filled
Power Macintosh Q650	601	66 MHz	integrated	integrated	33 MHz	64-bit	32K	1MB		68040, 66/33 MHz	3 NuBus, PDS filled
PowerBook Duo Dock II	none	n/a	n/a	68882	n/a	n/a	n/a	32K		n/a	2 NuBus
PowerBook Duo Dock Plus	none	n/a	n/a	none	n/a	n/a	n/a	none		n/a	2 NuBus
PowerBook G3 (FireWire)	G3	400, 500	integrated	integrated	160/200	64-bit	64K	1MB		none	1 Type I or Type II PC Card
PowerBook G3 Series 12.1" (233, 250 MHz)	G3	233/250	integrated	integrated	66/83	64-bit	64K	none		none	2 Type II PC Card (1Type III)
PowerBook G3 Series 12.1" (233 MHz)	G3	233	integrated	integrated	66/83	64-bit	64K	512K		none	2 Type II PC Card (1Type III)
PowerBook G3 Series 13.3" (233, 250, 292)	G3	233/250	integrated	integrated	66/83Mhz	64-bit	64K	(none)		none	2 Type II PC Card (1 Type
PowerBook G3 Series 14.1" (233, 250, 292)	G3	233/250/	integrated	integrated	66/83Mhz	64-bit	64K	none		none	2 Type II PC Card (1 Type
PowerBook G3 Series 14.1" (233, 266, 300)	G3	233/266/	integrated	integrated	66Mhz	64-bit	64K	512K		none	2 Type II PC Card (1 Type
PowerBook G3 Series (Bronze Keyboard, 2001)	G3	333 MHz	integrated	integrated	66/83	64-bit	64 K	512 K		none	1 Type II PC Card
PowerBook G3 Series (Bronze Keyboard, 2002)	G3	400 MHz	integrated	integrated	66/83Mhz	64-bit	64K	1 MB		none	1 Type II PC Card
PowerBook G4	G4	400/500	integrated	integrated	66/83Mhz	64-bit	64K	1 MB		none	1 Type II PC Card
PowerBook G4 (12")	G4	867MHz	integrated	integrated	133 Mhz	64-bit	64K	256K	1MB	none	1 Type II PC Card
PowerBook G4 (17")	G4	1GHz	integrated	integrated	333 Mhz	64-bit	64K	256K	1MB	none	1 Type II PC Card
PowerBook G4 (Early 2002)	G4	667/800	integrated	integrated	133 Mhz	64-bit	64K	256K	1MB	none	1 Type II PC Card
PowerBook G4 (Late 2001)	G4	550/667	integrated	integrated	100/133	64-bit	64K	256 K		none	1 Type II PC Card
PowerBook G4 (Late 2002)	G4	867	integrated	integrated	133 Mhz	64-bit	64K	256K	1MB	none	1 Type II PC Card
Radius System 100/110	601	110 MHz	none	none	40 MHz		32K	256K		none	3 NuBus, 1 PDS
Radius System 100/80	601	80 MHz	none	none	37 MHz		32K	256K		none	3 NuBus, 1 PDS
Radius System 81/110	601	110 MHz	none	none	37 MHz		32K	256K		none	3 NuBus, 1 PDS
Twentieth Anniversary Macintosh	603e	250 MHz	integrated	integrated	50 MHz	64-bit	32K	256K		none	1 PCI, Comm II
Umax SuperMac C500/140	603e	140 MHz	none	none	40 MHz		32K	256K-1		none	2 PCI
Umax SuperMac C500/160	603e	160 MHz	none	none	40 MHz		32K	256K-1		none	2 PCI
Umax SuperMac C500/180	603e	180 MHz	none	none	40 MHz		32K	256K-1		none	2 PCI
Umax SuperMac C500/200	603e	200 MHz	none	none	40 MHz		32K	256K-1		none	2 PCI
Umax SuperMac C500/240	603e	240 MHz	none	none	40 MHz		32K	256K-1		none	2 PCI
Umax SuperMac C600/180	603e	180 MHz	none	none	40 MHz		32K	256K-1		none	3 PCI
Umax SuperMac C600/200	603e	200 MHz	none	none	40 MHz		32K	256K-1		none	3 PCI
Umax SuperMac C600/240	603e	240 MHz	none	none	40 MHz		32K	256K-1		none	3 PCI
Umax SuperMac C600/280	603e	280 MHz	none	none	40 MHz		32K	256K-1		none	3 PCI
Umax SuperMac C600x/240	603e	240 MHz	none	none	40 MHz		32K	256K-1		none	3 PCI
Umax SuperMac C600x/280	603e	280 MHz	none	none	40 MHz		32K	256K-1		none	3 PCI
Umax SuperMac J700/150	604	150 MHz	none	none	50 MHz		32K	512K		none	4 PCI
Umax SuperMac J700/180	604e	180 MHz	none	none	50 MHz		32K	512K		none	4 PCI
Umax SuperMac J700/233	604e	233 MHz	none	none	50 MHz		32K	512K		none	4 PCI
Umax SuperMac J710/200	604e	233 MHz	none	none	40 MHz		32K	512K-1		none	2PCI
Umax SuperMac J710/G3	G3	240 MHz	none	none	50 MHz		32K	512K-1		none	2PCI
Umax SuperMac S900/150	604e	150 MHz	none	none	50 MHz		32K	512K-1		ASPD slot	6PCI
Umax SuperMac S900/180	604e	180 MHz	none	none	50 MHz		32K	512K-1		ASPD slot	6PCI
Umax SuperMac S900/180DP	604e	180 MHz	none	none	50 MHz		32K	512K-1		ASPD slot	6PCI
Umax SuperMac S900/200	604e	200 MHz	none	none	50 MHz		32K	512K-1		ASPD slot	6PCI
Umax SuperMac S900/200DP	604e	200 MHz	none	none	50 MHz		32K	512K-1		ASPD slot	6PCI
Umax SuperMac S900/225	604e	225 MHz	none	none	50 MHz		32K	512K-1		ASPD slot	6PCI
Umax SuperMac S900/233	604e	233 MHz	none	none	50 MHz		32K	512K-1		ASPD slot	6PCI
Umax SuperMac S900/250	604e	250 MHz	none	none	50 MHz		32K	512K-1		ASPD slot	6PCI
Umax SuperMac S900/250DP	604e	250 MHz	none	none	50 MHz		32K	512K-1		ASPD slot	6PCI
Umax SuperMac S900/G3	G3	250 MHz	none	none	50 MHz		32K	512K-1		ASPD slot	6PCI
Umax SuperMac S910	604e	250 MHz	none	none	50 MHz		32K	1MB		ASPD slot	6PCI
Workgroup Server 60	68040	40 MHz	integrated	integrated	20 MHz	32-bit	8K	none		none	one 7" NuBus or PDS
Workgroup Server 60 (50/25 MHz)	68040	50 MHz	integrated	integrated	25 MHz	32-bit	8K	none		none	one 7" NuBus or PDS
Workgroup Server 6150	601	60 MHz	integrated	integrated	30 MHz	64-bit	32K	256K		none	one 7" NuBus or PDS
Workgroup Server 6150/66	601	66 MHz	integrated	integrated	30 MHz	64-bit	32K	256K		none	one 7" NuBus or PDS
Workgroup Server 7250/120	601	120 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		none	3 PCI
Workgroup Server 7350/180	604e	180 MHz	integrated	integrated	45 MHz	64-bit	64K	256K		opt. PC Compatibility Card	3 PCI
Workgroup Server 80	68040	66 MHz	integrated	integrated	33 MHz	32-bit	8K	none		none	3 NuBus, 1 PDS
Workgroup Server 8150	601	80 MHz	integrated	integrated	40 MHz	64-bit	32K	256K		none	3 NuBus, 1 PDS
Workgroup Server 8150/110	601+	110 MHz	integrated	integrated	36.7 MHz	64-bit	32K	256K		none	3 NuBus, 1 PDS
Workgroup Server 8550/132	604	132 MHz	integrated	integrated	44 MHz	64-bit	32K	512K		none	3 PCI
Workgroup Server 8550/200	604e	200 MHz	integrated	integrated	50 MHz	64-bit	64K	512K		none	3 PCI
Workgroup Server 9150	601	80 MHz	integrated	integrated	40 MHz	64-bit	32K	512K		none	4 NuBus, 1 PDS
Workgroup Server 9150/120	601	120 MHz	integrated	integrated	40 MHz	64-bit	32K	1MB		none	4 NuBus, 1 PDS
Workgroup Server 95	68040	66 MHz	integrated	integrated	33 MHz	32-bit	8K	opt'l.		none	5 NuBus, 1 PDS
Workgroup Server 9650/233	604e	233 MHz	integrated	integrated	50 MHz	64-bit	64K	512K		opt. PC Compatibility Card	6 PCI
Workgroup Server 9650/350	604e	350 MHz	integrated	integrated	100 MHz	64-bit	64K	512K		opt. PC Compatibility Card	6 PCI
Xserve	G4	1/2 GHz	integrated	integrated	133 MHz	128-bit		256K	2MB	optional 1GHz G4	2 PCI, 1 PCI/AGP, 2