

## Memory

Name	Logic Board RAM	Min. RAM	Max. RAM	No. of Slots	Memory Type	Memory Speed	Memory Sizes	Install in Groups of
Apple I	8k		32k (65k)		expansion card			
Apple II	4k		64k		expansion card			
Apple II+	48k		64k		expansion card			
Apple II+ (Bell & Howell)	48k		64k		expansion card			
Apple IIc	128k		1 MB		expansion card			
Apple IIc Plus	128k		1 MB		expansion card			
Apple IIe	64k		128k		expansion card			
Apple IIe (extended/enhanced)	128k		128k		expansion card			
Apple IIgs	256k		8 MB		expansion card			
Apple III	128k		256k		expansion card			
Apple III+	128k		256k		expansion card			
DayStar Genesis LT 400+	16MB	24MB	1.5GB	12	168-pin DIMM	60 ns	32, 64, 128 MB	1
DayStar Genesis MP 300	16MB	24MB	1.5GB	12	168-pin DIMM	60 ns	32, 64, 128 MB	1
DayStar Genesis MP 360+	16MB	24MB	1.5GB	12	168-pin DIMM	60 ns	32, 64, 128 MB	1
DayStar Genesis MP 400+	16MB	24MB	1.5GB	12	168-pin DIMM	60 ns	32, 64, 128 MB	1
DayStar Genesis MP 450+	16MB	24MB	1.5GB	12	168-pin DIMM	60 ns	32, 64, 128 MB	1
DayStar Genesis MP 466+	16MB	24MB	1.5GB	12	168-pin DIMM	60 ns	32, 64, 128 MB	1
DayStar Genesis MP 528	16MB	24MB	1GB	8	168-pin DIMM	60 ns	32, 64, 128 MB	1
DayStar Genesis MP 600	16MB	24MB	1.5GB	12	168-pin DIMM	60 ns	32, 64, 128 MB	1
DayStar Genesis MP 720+	16MB	24MB	1.5GB	12	168-pin DIMM	60 ns	32, 64, 128 MB	1
DayStar Genesis MP 800+	16MB	24MB	1.5GB	12	168-pin DIMM	60 ns	32, 64, 128 MB	1
DayStar Genesis MP 900+	16MB	24MB	1.5GB	12	168-pin DIMM	60 ns	32, 64, 128 MB	1
DayStar Genesis MP 932+	16MB	24MB	1.5GB	12	168-pin DIMM	60 ns	32, 64, 128 MB	1
eMac	none	128	1 GB	2	PC100 DIMM	10 ns	128, 256, 512 MB	1
eMac (Late 2002)	none	128	1 GB	2	PC100 DIMM	10 ns	128, 256, 512 MB	1
eMate 300	8 MB	3 MB			PCMCIA card			
iBook		32 or	160 MB	1	SO-DIMM	10 ns	32,64,128, 256 MB	1
iBook 12.1" (2002)	128 MB	128	640 MB	1	PC100	10 ns	32,64,128, 256 MB	1
iBook 12.1" (Late 2002)	128 MB	128	640 MB	1	PC100	10 ns	32,64,128, 256 MB	1
iBook 14.1" (2002)	128 MB	128	640 MB	1	PC100	10 ns	32,64,128, 256 MB	1
iBook 14.1" (Late 2002)	256 MB	256	640 MB	1	PC100	10 ns	32,64,128, 256 MB	1
iBook (Dual-USB)	64/128	64 MB	640 MB	1	PC100	10 ns	32,64,128, 256 MB	1
iBook (Dual-USB/Late 2001)	128 MB	128	640 MB	1	PC100	10 ns	32,64,128, 256 MB	1
iBook (Mid 2002)	128 MB	128	640 MB	1	PC100	10 ns	32,64,128, 256 MB	1
iBook SE		64 MB	320 MB	1	SO-DIMM	10 ns	32,64,128, 256 MB	1
iBook/SE (FireWire)		32 or	160 MB	1	SO-DIMM	10 ns	32,64,128, 256 MB	1
iMac (5 Flavors, 266 MHz) "Rev. C"	none	32 MB	128 MB	2	SO-DIMM	10 ns	16, 32, 64, 128 MB	1
iMac (5 Flavors, 333 MHz) "Rev. D"	none	32 MB	128 MB	2	SO-DIMM	10 ns	16, 32, 64, 128 MB	1
iMac (500 MHz - Late 2001)	none	128	1 GB	2	PC100 DIMM	10 ns	32, 64, 128, 256, 512 MB	1
iMac (600 MHz - Late 2001)	none	256	1 GB	2	PC100 DIMM	10 ns	32, 64, 128, 256, 512 MB	1
iMac (Bondi Blue, 233 MHz)	none	32 MB	128 MB	2	SO-DIMM	10 ns	16, 32, 64, 128 MB	1
iMac DV SE (Summer 2000)	none	32 MB	1 GB	2	PC100 DIMM	10 ns	32, 64, 128, 256, 512 MB	1
iMac DV (Summer 2000)	none	32 MB	1 GB	2	PC100 DIMM	10 ns	32, 64, 128, 256, 512 MB	1
iMac DV+ (Summer 2000)	none	32 MB	1 GB	2	PC100 DIMM	10 ns	32, 64, 128, 256, 512 MB	1
iMac DV/SE	none	64 MB	512 MB	2	PC100 DIMM		64, 128, 256 MB	1
iMac (Early 2001)	none	32 MB	1 GB	2	PC100 DIMM	100	32, 64, 128, 256, 512 MB	1
iMac "Luxo" (700 MHz - LCD)	none	128 or	1 GB	1	SO-DIMM	100	32, 64, 128, 256, 512 MB	1
iMac "Luxo" (700 MHz - LCD - Summer 2002)	none	128 or	1 GB	1	SO-DIMM	100	32, 64, 128, 256, 512 MB	1
iMac "Luxo" (800 MHz - LCD)	none	256	1 GB	1	SO-DIMM	100	32, 64, 128, 256, 512 MB	1
iMac "Luxo" (800 MHz - LCD - Summer 2002)	none	256	1 GB	1	SO-DIMM	100	32, 64, 128, 256, 512 MB	1
iMac "Luxo" Widescreen (800 MHz - LCD)	none	256	1 GB	1	SO-DIMM	100	32, 64, 128, 256, 512 MB	1
iMac SE (Early 2001)	none	32 MB	1 GB	2	PC100 DIMM	100	32, 64, 128, 256, 512 MB	1
iMac Special Edition (700 MHz - Late 2001)	none	256	1 GB	2	PC100 DIMM	100	32, 64, 128, 256, 512 MB	1
iMac/iMac DV (Slot Loading CD-ROM )	none	64 MB	512 MB	2	PC100 DIMM		64, 128, 256 MB	1
Interactive Television Box								
Lisa/Lisa2	none	0.5 MB	2 MB	2	Lisa card	n/a	512 K	1
Macintosh 128K	0.125 MB	0.125M	0.125 MB	0	n/a	n/a	n/a	n/a
Macintosh 512K	0.5 MB	0.5 MB	0.5 MB	0	n/a	n/a	n/a	n/a
Macintosh 512Ke	0.5 MB	0.5 MB	0.5 MB	0	n/a	n/a	n/a	n/a
Macintosh Centris 610	4 MB	4 MB	68 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Centris 650	4, 8 MB	4 MB	132, 136 M	4	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Centris 660AV	4 MB	4 MB	68 MB	2	72-pin SIMM	70 ns	4, 8, 16, 32 MB	1
Macintosh Classic	1 MB	1 MB	4 MB	2	30-pin SIMM	120 ns	256 K, 1 MB	2
Macintosh Classic II	2 MB	2 MB	10 MB	2	30-pin SIMM	100 ns	1, 2, 4 MB	2
Macintosh Color Classic	4 MB	4 MB	10MB	2	30-pin SIMM	100 ns	1, 2, 4 MB	2
Macintosh Color Classic II	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Duo Dock	none	n/a	n/a	0	n/a	n/a	n/a	n/a
Macintosh Duo Dock II	none	n/a	n/a	0	n/a	n/a	n/a	n/a
Macintosh Duo Dock Plus	none	n/a	n/a	0	n/a	n/a	n/a	n/a
Macintosh Duo MiniDock	none	n/a	n/a	0	n/a	n/a	n/a	n/a
Macintosh II	none	1 MB	20 MB	8	30-pin SIMM	120 ns	256 K, 1, 4 MB	4
Macintosh IIci	none	1 MB	128 MB	8	30-pin SIMM	80 ns	256 K, 512 K, 1, 2, 4, 16	4
Macintosh IIcx	none	1 MB	128 MB	8	30-pin SIMM	120 ns	256 K, 1, 4, 16 MB	4
Macintosh IIfx	none	4 MB	128 MB	8	64-pin SIMM	80 ns	1, 4, 16 MB	4
Macintosh IIsi	1 MB	1 MB	17 MB	4	30-pin SIMM	100 ns	256 K, 512 K, 1, 2, 4 MB	4
Macintosh IIvi	4 MB	4 MB	68 MB	4	30-pin SIMM	80 ns	256K, 1, 2, 4, 16 MB	4
Macintosh IIvx	4 MB	4 MB	68 MB	4	30-pin SIMM	80 ns	256K, 1, 2, 4, 16 MB	4
Macintosh IIx	none	1 MB	32 MB	8	30-pin SIMM	120 ns	256 K, 1, 4 MB	4
Macintosh LC	2 MB	2 MB	10 MB	2	30-pin SIMM	100 ns	1, 2, 4 MB	2

## Memory

Name	Logic Board RAM	Min. RAM	Max. RAM	No. of Slots	Memory Type	Memory Speed	Memory Sizes	Install in Groups of
Macintosh LC 475	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh LC 520	4MB B	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh LC 550	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh LC 575	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh LC 580	4 MB	8 MB	52 MB	2	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh LC 630	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh LC 630 DOS Compatible	8MB	12 MB	52 MB	2	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh LC II	4 MB	4 MB	10 MB	2	30-pin SIMM	100 ns	1, 2, 4 MB	2
Macintosh LC III	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh LC III+	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 200	2 MB	2 MB	10 MB	2	30-pin SIMM	100 ns	1, 2, 4 MB	2
Macintosh Performa 250	4 MB	4 MB	10 MB	2	30-pin SIMM	100 ns	1, 2, 4 MB	2
Macintosh Performa 275	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 400	4 MB	4 MB	10 MB	2	30-pin SIMM	100 ns	1, 2, 4 MB	2
Macintosh Performa 405	4 MB	4 MB	10 MB	2	30-pin SIMM	100 ns	1, 2, 4 MB	2
Macintosh Performa 410	4 MB	4 MB	10 MB	2	30-pin SIMM	100 ns	1, 2, 4 MB	2
Macintosh Performa 430	4 MB	4 MB	10 MB	2	30-pin SIMM	100 ns	1, 2, 4 MB	2
Macintosh Performa 450	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 460	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 466	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 467	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 475	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 476	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 520	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 5200CD	none	8 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 5210CD	none	8 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 5215CD	none	8 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 5220CD	none	8 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 5260/120	none	16 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 5260CD	none	8 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 5270CD	none	8 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 5280	none	16 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 5300CD	none	16 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 5320CD	none	16 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 5400/160	8 MB	16 MB	136 MB	2	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Macintosh Performa 5400/180	8 MB	16 MB	136 MB	2	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Macintosh Performa 5400CD	8 MB	16 MB	136 MB	2	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Macintosh Performa 5410CD	8 MB	16 MB	136 MB	2	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Macintosh Performa 5420CD	8 MB	16 MB	136 MB	2	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Macintosh Performa 5430	8 MB	16 MB	136 MB	2	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Macintosh Performa 5440	8 MB	16 MB	136 MB	2	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Macintosh Performa 550	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 560	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 575	4 MB	5 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 577	4 MB	5 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 578	4 MB	8 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 580CD	4 MB	8 MB	52 MB	2	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 588CD	4 MB	8 MB	52 MB	2	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 600 and 600CD	4 MB	4 MB	68 MB	4	30-pin SIMM	80 ns	256 K, 1, 2, 4, 16 MB	4
Macintosh Performa 6110CD	8 MB	8 MB	72 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Macintosh Performa 6112CD	8 MB	8 MB	72 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Macintosh Performa 6115CD	8 MB	8 MB	72 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Macintosh Performa 6116CD	8 MB	8 MB	72 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Macintosh Performa 6117CD	8 MB	8 MB	72 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Macintosh Performa 6118CD	8 MB	8 MB	72 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Macintosh Performa 6200CD	none	8 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 6205CD	none	8 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 6210CD	none	16 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 6214CD	none	8 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 6216CD	none	8 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 6218CD	none	16 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 6220CD	none	16 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 6230CD	none	16 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 6260CD	none	8 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 6290CD	none	8 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 630 and 630CD	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 6300CD	none	16 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 630CD DOS Compatible	4 MB	8 MB	52 MB	2	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 6310CD	none	16 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 631CD	4 MB	8 MB	52 MB	2	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 6320CD	none	16 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Performa 635CD	4 MB	5 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 636 and 636CD	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 6360	8 MB	16 MB	136 MB	2	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Macintosh Performa 637CD	4 MB	8 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 638CD	4 MB	8 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Performa 6400/180	8 MB	16MB	136 MB	2	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Macintosh Performa 6400/200	8 MB	16 MB	136 MB	2	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Macintosh Performa 640CD DOS Compatible	4 MB	8 MB	52 MB	2	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1

## Memory

Name	Logic Board RAM	Min. RAM	Max. RAM	No. of Slots	Memory Type	Memory Speed	Memory Sizes	Install in Groups of
Macintosh Performa 6410	8 MB	16 MB	136 MB	2	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Macintosh Performa 6420	8 MB	24 MB	136 MB	2	168-pin DIMM	70 ns	8, 16, 32, 64MB	1
Macintosh Plus	none	1 MB	4 MB	4	30-pin SIMM	150 ns	256 K, 1 MB	2
Macintosh Portable	1 MB	1MB	8 MB	1	SRAM card	30 ns	1-8 MB	1
Macintosh PowerBook 100	2 MB	2 MB	8 MB	1	PB1xx	100 ns	2, 4, 6 MB	1
Macintosh PowerBook 140	2 MB	2 MB	8 MB	1	PB1xx	100 ns	2, 4, 6 MB	1
Macintosh PowerBook 1400c/117	16MB	32 MB	64 MB	1	PB1400	70 ns	8-24 MB	1
Macintosh PowerBook 1400c/133	16 MB	16 MB	64 MB	1	PB1400	70 ns	8-24 MB	1
Macintosh PowerBook 1400c/166	16 MB	16 MB	64 MB	1	PB1400	70 ns	8-24MB	1
Macintosh PowerBook 1400cs/117	12, 16	12 MB	64 MB	1	PB1400	70 ns	8-24 MB	1
Macintosh PowerBook 1400cs/133	16 MB	16 MB	64 MB	1	PB1400	70 ns	8-24 MB	1
Macintosh PowerBook 1400cs/166	16 MB	16 MB	64 MB	1	PB1400	70 ns	8-24 MB	1
Macintosh PowerBook 145	2 MB	2 MB	8 MB	1	PB1xx	100 ns	2, 4, 6 MB	1
Macintosh PowerBook 145B	4 MB	4 MB	8 MB	1	PB1xx	100 ns	2, 4 MB	1
Macintosh PowerBook 150	4 MB	4 MB	40 MB	1	Duo	70 ns	4, 8, 20, 36 MB	1
Macintosh PowerBook 160	4 MB	4 MB	14 MB	1	PB1xx	85 ns	2, 4, 10 MB	1
Macintosh PowerBook 165	4 MB	4 MB	14 M B	1	PB1xx	85 ns	2, 4, 10 MB	1
Macintosh PowerBook 165c	4 MB	4 MB	14 MB	1	PB1xx	85 ns	2, 4, 10 MB	1
Macintosh PowerBook 170	2 MB	2 MB	8 MB	1	PB1xx	100 ns	2, 4, 6 MB	1
Macintosh PowerBook 180	4 MB	4 MB	14 MB	1	PB1xx	85 ns	2, 4, 6, 8, 10 MB	1
Macintosh PowerBook 180c	4 MB	4 MB	14 MB	1	PB1xx	85 ns	2, 4, 6, 8, 10 MB	1
Macintosh PowerBook 190/66	4, 8 MB	4 MB	36, 40 MB	1	PB53xx	70 ns	4-32 MB	1
Macintosh PowerBook 190cs/66	4, 8 MB	4 MB	36, 40 MB	1	PB53xx	70 ns	4-32 MB	1
Macintosh PowerBook 2400c/180	16 MB	16 MB	48 MB	1	SO-DIMM	n/a	n/a	1
Macintosh PowerBook 2400c/240	16 MB	16 MB	80 M B	1	SO-DIMM	n/a	n/a	1
Macintosh PowerBook 3400c/180	16 MB	16 MB	144 MB	1	PB 3400	60 ns	4-128 MB	1
Macintosh PowerBook 3400c/200	16 MB	16 MB	144 MB	1	PB 3400	60 ns	4-128 MB	1
Macintosh PowerBook 3400c/240	16 MB	16 MB	144 MB	1	PB 3400	60 ns	4-128 MB	1
Macintosh PowerBook 500 with PowerPC	8 MB	8 MB	40 MB	1	PB5xx	70 ns	4, 8, 12, 20, 32 MB	1
Macintosh PowerBook 520	4 MB	4 MB	36 MB	1	PB5xx	70 ns	4, 8, 12, 20, 32 MB	1
Macintosh PowerBook 520c	4 MB	4 MB	36 MB	1	PB5xx	70 ns	4, 8, 12, 20, 32 MB	1
Macintosh PowerBook 5300/100	8 MB	8 MB	64 MB	1	PB53xx	70 ns	8-56 MB	1
Macintosh PowerBook 5300c/100	8, 16 MB	8 MB	64 MB	1	PB53xx	70 ns	8-64 MB	1
Macintosh PowerBook 5300ce/117	16 MB	32 MB	64 MB	1	PB53xx	70 ns	8-64 MB	1
Macintosh PowerBook 5300cs/100	8, 16 MB	8 MB	64 MB	1	PB53xx	70 ns	8-64 MB	1
Macintosh PowerBook 540	4 MB	4 MB	36 MB	1	PB5xx	70 ns	4, 8, 12, 20, 32 MB	1
Macintosh PowerBook 540c	4 MB	4 MB	36 MB	1	PB5xx	70 ns	4, 8, 12, 20, 32 MB	1
Macintosh PowerBook 550c	4 MB	12 MB	36 MB	1	PB5xx	70 ns	4, 8, 12, 20, 32 MB	1
Macintosh PowerBook Duo 210	4 MB	4 MB	24 MB	1	Duo	70 ns	4-20 MB	1
Macintosh PowerBook Duo 230	4 MB	4 MB	24 MB	1	Duo	70 ns	4-20 MB	1
Macintosh PowerBook Duo 2300c/100	8 MB	8 MB	56 MB	1	Duo	70 ns	4-48 MB	1
Macintosh PowerBook Duo 250	4 MB	4 MB	24 MB	1	Duo	70 ns	4-20 MB	1
Macintosh PowerBook Duo 270c	4 MB	4 MB	32 MB	1	Duo	70 ns	4-28 MB	1
Macintosh PowerBook Duo 280	4 MB	4 MB	40 MB	1	Duo	70 ns	4-36 MB	1
Macintosh PowerBook Duo 280c	4 MB	4 MB	40 M B	1	Duo	70 ns	4-36 MB	1
Macintosh PowerBook G3	32 MB	32 MB	160 MB	1	PB G3	60 ns	4-128 MB	1
Macintosh Quadra 605	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Quadra 610	4 MB	4 MB	68 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Quadra 610 DOS Compatible	4 MB	4 MB	68 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Quadra 630	4 M B	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Macintosh Quadra 650	4, 8 MB	4 MB	132, 136 M	4	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Macintosh Quadra 660AV	4 MB	4 MB	68 MB	2	72-pin SIMM	70 ns	4, 8, 16, 32 MB	1
Macintosh Quadra 700	4 MB	4 MB	20 MB	4	30-pin SIMM	80 ns	1, 4 MB	4
Macintosh Quadra 800	8 MB	8 MB	136MB	4	72-pin SIMM	60 ns	4, 8, 16, 32 MB	1
Macintosh Quadra 840AV	none	4 MB	128 MB	4	72-pin SIMM	60 ns	4, 8, 16, 32 MB	1
Macintosh Quadra 900	none	4 MB	256 MB	16	30-pin SIMM	80 ns	1, 4, 8, 16 MB	4
Macintosh Quadra 950	none	4 MB	256 MB	16	30-pin SIMM	80 ns	1, 4, 8, 16 MB	4
Macintosh SE	none	1 MB	4 MB	4	30-pin SIMM	150 ns	256 K, 1 MB	2
Macintosh SE FDHD	none	1 MB	4 MB	4	30-pin SIMM	150 ns	256 K, 1 MB	2
Macintosh SE/30	none	1 MB	32 MB	8	30-pin SIMM	120 ns	256 K, 1, 4 MB	4
Macintosh Server G3	none	32 MB	384 MB	3	168-pin DIMM	10 ns	8, 16, 32, 64, 128 MB	1
Macintosh Server G4 with AppleShare IP	none	128	1.5 GB	4	PC100 DIMM	100	64, 128, 256, 512 MB	1
Macintosh Server G4 with Mac OS X Server	none	256	1 GB	4	PC100 DIMM	100	64, 128, 256, 512 MB	1
Macintosh TV	4 MB	4 MB	8 M B	1	72-pin SIMM	80 ns	1, 4 MB	1
Macintosh XL	none	0.5 MB	2 MB	2	Lisa card	n/a	512 K	1
Motorola StarMax 3000/160		16 or	160 MB	3	168-pin DIMM	60 ns	32, 64 MB	1
Motorola StarMax 3000/180		16 or	160 MB	3	168-pin DIMM	60 ns	32, 64 MB	1
Motorola StarMax 3000/200		16 or	160 MB	3	168-pin DIMM	60 ns	32, 64 MB	1
Motorola StarMax 3000/240		16 or	160 MB	3	168-pin DIMM	60 ns	32, 64 MB	1
Motorola StarMax 4000/160		16 or	160 MB	3	168-pin DIMM	60 ns	32, 64 MB	1
Motorola StarMax 4000/200		16 or	160 MB	3	168-pin DIMM	60 ns	32, 64 MB	1
Motorola StarMax 5000/225		16 or	160 MB	3	168-pin DIMM	60 ns	32, 64 MB	1
Motorola StarMax 5000/250		16 or	160 MB	3	168-pin DIMM	60 ns	32, 64 MB	1
Motorola StarMax 5000/275		16 or	160 MB	3	168-pin DIMM	60 ns	32, 64 MB	1
Motorola StarMax 5000/300		16 or	160 MB	3	168-pin DIMM	60 ns	32, 64 MB	1
Motorola StarMax 5500/200		16 or	160 MB	3	168-pin DIMM	60 ns	32, 64 MB	1
Network Server 500/132	none	32 MB	512 MB	8	168-pin DIMM	60 ns	8, 16, 32, 64 MB	2
Network Server 700/150	none	32 MB	512 MB	8	168-pin DIMM	60 ns	8, 16, 32, 64 MB	2
Network Server 700/200	none	48 MB	512 MB	8	168-pin DIMM	60 ns	8, 16, 32, 64 MB	2



## Memory

Name	Logic Board RAM	Min. RAM	Max. RAM	No. of Slots	Memory Type	Memory Speed	Memory Sizes	Install in Groups of
Newton MessagePad 100	4 MB	640 K						
Newton MessagePad 110	4 MB	1 MB			PCMCIA card			
Newton MessagePad 120a	8 MB	1 MB			PCMCIA card			
Newton MessagePad 120b	8 MB	2 MB			PCMCIA card			
Newton MessagePad 130	8 MB	2.5 MB			PCMCIA card			
Newton MessagePad 2000	8 MB	5 MB			PCMCIA card			
Newton MessagePad 2100	8 MB	8 MB			PCMCIA card			
Newton MessagePad (Original MessagePad	4 MB	640 K						
NeXT Cube	128 K	8 MB	64 MB					
NeXTcube	128 K	16 MB	64 MB					
NeXTdimension	128 K	24 MB	64 MB					
NeXTstation	128 KB	8 MB	32 MB					
NeXTstation Color	128 KB	12 MB	32 MB					
Pippin	128 K	6 MB					2, 4, 8 MB	
Power Computing Power 100 Desktop	16MB	16MB	200MB	8	72-pin SIMM	80 ns	16 MB	
Power Computing Power 100 Tower	16MB	16MB	200MB	8	72-pin SIMM	80 ns	16 MB	
Power Computing Power 120 Desktop	16MB	16MB	200MB	8	72-pin SIMM	80 ns	16 MB	
Power Computing Power 120 Tower	16MB	16MB	200MB	8	72-pin SIMM	80 ns	16 MB	
Power Computing Power 80 Desktop	16MB	16MB	200MB	8	72-pin SIMM	80 ns	16 MB	
Power Computing Power 80 Tower	16MB	16MB	200MB	8	72-pin SIMM	80 ns	16 MB	
Power Computing PowerBase 180 Low	16MB	16MB	160MB	3	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerBase 180 Tower	16MB	16MB	160MB	3	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerBase 200 Low	16MB	16MB	160MB	3	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerBase 200 Tower	16MB	16MB	160MB	3	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerBase 240 Low	16MB	16MB	160MB	3	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerBase 240 Tower	16MB	16MB	160MB	3	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerCenter 120 Desktop	8MB	8MB	256MB	4	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerCenter 120 Low	8MB	8MB	256MB	4	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerCenter 120 Tower	8MB	8MB	256MB	4	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerCenter 132 Desktop	8MB	8MB	256MB	4	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerCenter 132 Low	8MB	8MB	256MB	4	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerCenter 132 Tower	8MB	8MB	256MB	4	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerCenter 140 Low	8MB	8MB	256MB	4	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerCenter 140 Tower	8MB	8MB	256MB	4	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerCenter 150 Desktop	8MB	8MB	256MB	4	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerCenter 166 Desktop	8MB	8MB	256MB	4	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerCenter 166 Low	8MB	8MB	256MB	4	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerCenter 166 Tower	8MB	8MB	256MB	4	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerCenter 180 Desktop	8MB	8MB	256MB	4	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerCenter 180 Low	8MB	8MB	256MB	4	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerCenter 180 Tower	8MB	8MB	256MB	4	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerCenter 210 Desktop	8MB	8MB	256MB	4	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerCenter 210 Low	8MB	8MB	256MB	4	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerCenter 210 Tower	8MB	8MB	256MB	4	168-pin DIMM	70 ns	32, 64 MB	1
Power Computing PowerCenter Pro 180	16MB	16MB	512MB	4	168-pin DIMM	60 ns	32, 64, 128 MB	1
Power Computing PowerCenter Pro 180	16MB	16MB	512MB	4	168-pin DIMM	60 ns	32, 64, 128 MB	1
Power Computing PowerCenter Pro 210	16MB	16MB	512MB	4	168-pin DIMM	60 ns	32, 64, 128 MB	1
Power Computing PowerCenter Pro 210	16MB	16MB	512MB	4	168-pin DIMM	60 ns	32, 64, 128 MB	1
Power Computing PowerCenter Pro 240	16MB	16MB	512MB	4	168-pin DIMM	60 ns	32, 64, 128 MB	1
Power Computing PowerCenter Pro 240	16MB	16MB	512MB	4	168-pin DIMM	60 ns	32, 64, 128 MB	1
Power Computing PowerCurve 120	8MB	8MB	256MB	4	168-pin DIMM	70 ns	16, 32, 64 MB	
Power Computing PowerTower 166	8MB	8MB	256MB	4	168-pin DIMM	60 ns	32, 64 MB	1
Power Computing PowerTower 180	8MB	8MB	256MB	4	168-pin DIMM	60 ns	32, 64 MB	1
Power Computing PowerTower 200	8MB	8MB	256MB	4	168-pin DIMM	60 ns	32, 64 MB	1
Power Computing PowerTower Pro 180	16MB	16MB	1GB	8	168-pin DIMM	70 ns	32, 64, 128 MB	1
Power Computing PowerTower Pro 200	16MB	16MB	1GB	8	168-pin DIMM	70 ns	32, 64, 128 MB	1
Power Computing PowerTower Pro 225	16MB	16MB	1GB	8	168-pin DIMM	70 ns	32, 64, 128 MB	1
Power Computing PowerTower Pro 250	16MB	16MB	1GB	8	168-pin DIMM	70 ns	32, 64, 128 MB	1
Power Computing PowerWave 120 Desktop	16MB	16MB	512MB	4	168-pin DIMM	70 ns	32, 64, 128 MB	1
Power Computing PowerWave 120 Tower	16MB	16MB	512MB	4	168-pin DIMM	70 ns	32, 64, 128 MB	1
Power Computing PowerWave 132 Desktop	16MB	16MB	512MB	4	168-pin DIMM	70 ns	32, 64, 128 MB	1
Power Computing PowerWave 132 Tower	16MB	16MB	512MB	4	168-pin DIMM	70 ns	32, 64, 128 MB	1
Power Computing PowerWave 150 Desktop	16MB	16MB	512MB	4	168-pin DIMM	70 ns	32, 64, 128 MB	1
Power Computing PowerWave 150 Tower	16MB	16MB	512MB	4	168-pin DIMM	70 ns	32, 64, 128 MB	1
Power Mac G4 - AGP Graphics	none	64 MB	1.5 GB	4	PC100 DIMM	100	32, 64, 128, 256, 512 MB	1
Power Mac G4 Cube	none	64 MB	1.5 GB	3	PC100 DIMM	100	64, 128, 256, 512 MB	1
Power Mac G4 (Digital Audio)	none	64 MB	1.5 GB	3	PC133 DIMM	100	64, 128, 256, 512 MB	1
Power Mac G4 (Gigabit Ethernet)	none	64 MB	1.5 GB	4	PC100 DIMM	100	64, 128, 256, 512 MB	1
Power Mac G4 (Mirrored Drive Doors - Late	none	256/51	2 GB	3	PC2100 DDR	2100	128, 256, 512 MB	1
Power Mac G4 - PCI Graphics	none	64 MB	1 GB	4	PC100 DIMM	100	32, 64, 128, 256, 512 MB	1
Power Mac G4 (Quick Silver)	none	128/25	1.5 GB	3	PC133 DIMM	100	128, 256, 512 MB	1
Power Mac G4 (Quick Silver - Early 2002)	none	256/51	1.5 GB	3	PC133 DIMM	100	128, 256, 512 MB	1
Power Macintosh 4400/160	none	16 M B	96 MB	3	168-pin DIMM	60 ns	8, 16, 32 MB	1
Power Macintosh 4400/200	none	16 MB	160 MB	3	168-pin DIMM	60 ns	8, 16, 32, 64 MB	1
Power Macintosh 4400/200 PC Compatible	none	32 MB	160 MB	3	168-pin DIMM	60 ns	8, 16, 32, 64 MB	1
Power Macintosh 475/605	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Power Macintosh 5200/75 LC	none	8 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Power Macintosh 5260/100	none	16 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Power Macintosh 5260/120	none	16 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1

## Memory

Name	Logic Board RAM	Min. RAM	Max. RAM	No. of Slots	Memory Type	Memory Speed	Memory Sizes	Install in Groups of
Power Macintosh 5300/100 LC	none	16 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Power Macintosh 5400/120	8MB	16 MB	136 MB	2	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 5400/180	8 MB	16 MB	136 MB	2	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 5400/200	8 MB	24 MB	136 MB	2	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 5500/225	none	32 MB	128 MB	2	168-pin DIMM	60 ns	4, 8, 16, 32, 64 MB	1
Power Macintosh 5500/250	none	32 MB	128 MB	2	168-pin DIMM	60 ns	4, 8, 16, 32, 64 MB	1
Power Macintosh 575	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Power Macintosh 580	4 MB	4 MB	52 MB	2	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Power Macintosh 6100/60	8 MB	8 MB	72 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Power Macintosh 6100/60AV	8 MB	8 MB	72 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Power Macintosh 6100/66	8 MB	8 MB	72 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Power Macintosh 6100/66 DOS Compatible	8 MB	8 MB	72 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Power Macintosh 6100/66AV	8 MB	8 MB	72 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Power Macintosh 6200/75	none	8 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Power Macintosh 630	4 MB	4 MB	36 MB	1	72-pin SIMM	80 ns	1, 2, 4, 8, 16, 32 MB	1
Power Macintosh 6300/120	none	16 MB	64 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Power Macintosh 6300/160	8 MB	16 MB	136 MB	2	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 6400/180	8 MB	16 MB	136 MB	2	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 6400/200	8 MB	16 MB	136 MB	2	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 6500/225	none	32 MB	128 MB	2	168-pin DIMM	60 ns	4, 8, 16, 32, 64 MB	1
Power Macintosh 6500/250	none	32 MB	128 MB	2	168-pin DIMM	60 ns	4, 8, 16, 32, 64 MB	1
Power Macintosh 6500/275	none	32 MB	128 MB	2	168-pin DIMM	60 ns	4, 8, 16, 32, 64 MB	1
Power Macintosh 6500/300	none	64 MB	128 MB	2	168-pin DIMM	60 ns	4, 8, 16, 32, 64 MB	1
Power Macintosh 700	4 MB	4 MB	20 MB	4	30-pin SIMM	80 ns	1, 4 MB	4
Power Macintosh 7100/66	8 MB	8 MB	136 MB	4	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Power Macintosh 7100/66AV	8 MB	8 MB	136 MB	4	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Power Macintosh 7100/80	8 MB	8 MB	136 MB	4	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Power Macintosh 7100/80AV	8 MB	8 MB	136 MB	4	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Power Macintosh 7200/120	none	8 MB	256 MB	4	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 7200/120 PC Compatible	none	8 MB	256 MB	4	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 7200/75	none	8 MB	256 MB	4	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 7200/90	none	8 MB	256 MB	4	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 7215/90	none	16 MB	256 MB	4	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 7220/200	none	16 MB	160 MB	3	168-pin DIMM	60 ns	8, 16, 32, 64 MB	1
Power Macintosh 7220/200 PC Compatible	none	32 MB	160 MB	3	168-pin DIMM	60 ns	8, 16, 32, 64 MB	1
Power Macintosh 7300/166	none	16 MB	512 MB	8	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 7300/180	none	16 MB	512 MB	8	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 7300/180 PC Compatible	none	32 MB	512 MB	8	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 7300/200	none	32 MB	512 MB	8	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 7500/100	none	8 MB	512 MB	8	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 7600/120	none	8 MB	512 MB	8	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 7600/132	none	8 MB	512 MB	8	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 7600/200	none	32 MB	512 MB	8	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 800	8 MB	8 MB	136 MB	4	72-pin SIMM	60 ns	4, 8, 16, 32 MB	1
Power Macintosh 8100/100	8 MB	8 MB	264 MB	8	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Power Macintosh 8100/100AV	8 MB	8 MB	264 MB	8	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Power Macintosh 8100/110	8 MB	16 MB	264 MB	8	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Power Macintosh 8100/80	8 MB	8 MB	264 MB	8	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Power Macintosh 8100/80AV	8 MB	8 MB	264 MB	8	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Power Macintosh 8115/110	8 MB	8 MB	264 MB	8	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Power Macintosh 8200/100	none	8 MB	256 MB	4	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 8200/120	none	16 MB	256 MB	4	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 8500/120	none	16 MB	512 MB	8	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 8500/132	none	16 MB	512 MB	8	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 8500/150	none	16 MB	512 MB	8	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 8500/180	none	16 MB	512 MB	8	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 8515/120	none	32 MB	512 MB	8	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 8600/200	none	32 MB	512 MB	8	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 8600/250	none	32 MB	512 MB	8	168-pin DIMM	70 ns	8, 16, 32, 64MB	1
Power Macintosh 8600/300	none	32 MB	512 MB	8	168-pin DIMM	70 ns	8, 16, 32, 64MB	1
Power Macintosh 900	none	4 MB	256 MB	16	30-pin SIMM	80 ns	1, 4, 8, 16 MB	4
Power Macintosh 950	none	4 MB	256 MB	16	30-pin SIMM	80 ns	1, 4, 8, 16 MB	4
Power Macintosh 9500/120	none	16 MB	768 MB	12	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 9500/132	none	16 MB	768 MB	12	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 9500/150	none	8 MB	768 MB	12	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 9500/180MP	none	32 MB	768 MB	12	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 9500/200	none	16 MB	768 MB	12	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 9515/132	none	8 MB	768 MB	12	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 9600/200	none	32 MB	768 MB	12	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 9600/200MP	none	32 MB	768 MB	12	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 9600/233	none	32 MB	768 MB	12	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Power Macintosh 9600/300	none	64 MB	768 MB	12	168-pin DIMM	70 ns	8, 16, 32, 64MB	1
Power Macintosh 9600/350	none	64 MB	768 MB	12	168-pin DIMM	70 ns	8, 16, 32, 64MB	1
Power Macintosh C610	4M B	4 MB	68 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Power Macintosh C650	4, 8 MB	4 MB	132, 136	4	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Power Macintosh G3 All-In-One	none	32 MB	384 MB	3	168-pin DIMM	10 ns	8, 16, 32, 64, 128 MB	1
Power Macintosh G3 (Blue and White)	none	64 MB	1 GB	4	PC100 DIMM		8, 16, 32, 64, 128, 256 MB	1
Power Macintosh G3 Desktop	none	32 MB	192 MB	3	168-pin DIMM	10 ns	8,16,32,64,128 MB	1
Power Macintosh G3 Mini Tower	none	32 MB	384 MB	3	168-pin DIMM	10 ns	8,16,32,64,128 MB	1

## Memory

Name	Logic Board RAM	Min. RAM	Max. RAM	No. of Slots	Memory Type	Memory Speed	Memory Sizes	Install in Groups of
Power Macintosh Q610	4 MB	4 MB	68 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Power Macintosh Q650	4, 8 MB	4 MB	132, 136	4	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
PowerBook Duo Dock II	none	n/a	n/a	0	n/a	n/a	n/a	n/a
PowerBook Duo Dock Plus	none	n/a	n/a	0	n/a	n/a	n/a	n/a
PowerBook G3 (FireWire)	none	64 MB	512 MB	2	PC100	10 ns	Up to 256 MB	1
PowerBook G3 Series 12.1" (233, 250 MHz)	none	32 MB	192 MB	2	144-pin	10 ns	32MB, 64MB, 128 MB	1
PowerBook G3 Series 12.1" (233 MHz)	none	32 MB	192 MB	2	144-pin	10 ns	32MB, 64MB, 128 MB	1
PowerBook G3 Series 13.3" (233, 250, 292)	none	32 MB	192 MB	2	144-pin	10 ns	32MB, 64MB, 128 MB	1
PowerBook G3 Series 14.1" (233, 250, 292)	none	32 MB	192 MB	2	144-pin	10 ns	32MB, 64MB, 128 MB	1
PowerBook G3 Series 14.1" (233, 266, 300)	none	32 MB	192 MB	2	144-pin	10 ns	32MB, 64MB, 128 MB	1
PowerBook G3 Series (Bronze Keyboard, 2001)	none	64 MB	384 MB	2	SO-DIMM	10 ns	64, 128, 256 MB	1
PowerBook G3 Series (Bronze Keyboard, 2002)	none	64 MB	384 MB	2	SO-DIMM	10 ns	64, 128, 256 MB	1
PowerBook G4	none	64 MB	1 GB	2	PC100 DIMM	10 ns	64, 128, 256, 512 MB	1
PowerBook G4 (12")	none	256	640 MB	2	PC2100 DDR	10 ns	128, 256, 512 MB	1
PowerBook G4 (17")	none	512	1 GB	2	PC2700 DDR	10 ns	512 MB	1
PowerBook G4 (Early 2002)	none	256/51	1 GB	2	PC133 DIMM	10 ns	64, 128, 256, 512 MB	1
PowerBook G4 (Late 2001)	none	128	1 GB	2	PC100 DIMM	10 ns	64, 128, 256, 512 MB	1
PowerBook G4 (Late 2002)	none	256/51	1 GB	2	PC133 DIMM	10 ns	64, 128, 256, 512 MB	1
Radius System 100/110	8MB	8MB	264MB	8	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Radius System 100/80	8MB	8MB	264MB	8	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Radius System 81/110	8MB	8MB	264MB	8	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Twentieth Anniversary Macintosh	none	32 MB	128 MB	2	168-pin DIMM	60 ns	4, 8, 16, 32, 64 MB	1
Umax SuperMac C500/140	16MB	16 or	144 MB	2	168-pin DIMM	70 ns	32, 64 MB	1
Umax SuperMac C500/160	16MB	16 or	144 MB	2	168-pin DIMM	70 ns	32, 64 MB	1
Umax SuperMac C500/180	16MB	16 or	144 MB	2	168-pin DIMM	70 ns	32, 64 MB	1
Umax SuperMac C500/200	16MB	16 or	144 MB	2	168-pin DIMM	70 ns	32, 64 MB	1
Umax SuperMac C500/240	16MB	16 or	144 MB	2	168-pin DIMM	70 ns	32, 64 MB	1
Umax SuperMac C600/180	16MB	16 or	144 MB	2	168-pin DIMM	70 ns	32, 64 MB	1
Umax SuperMac C600/200	16MB	16 or	144 MB	2	168-pin DIMM	70 ns	32, 64 MB	1
Umax SuperMac C600/240	16MB	16 or	144 MB	2	168-pin DIMM	70 ns	32, 64 MB	1
Umax SuperMac C600/280	16MB	16 or	144 MB	2	168-pin DIMM	70 ns	32, 64 MB	1
Umax SuperMac C600x/240	16MB	16 or	144 MB	2	168-pin DIMM	70 ns	32, 64 MB	1
Umax SuperMac C600x/280	16MB	16 or	144 MB	2	168-pin DIMM	70 ns	32, 64 MB	1
Umax SuperMac J700/150	16MB	24MB	1GB	8	168-pin DIMM	70 ns	32, 64, 128 MB	1
Umax SuperMac J700/180	16MB	24MB	1GB	8	168-pin DIMM	70 ns	32, 64, 128 MB	1
Umax SuperMac J700/233	16MB	24MB	1GB	8	168-pin DIMM	70 ns	32, 64, 128 MB	1
Umax SuperMac J710/200	16MB	24MB	144MB	3	168-pin DIMM	70 ns	32, 64, 128 MB	1
Umax SuperMac J710/G3	16MB	24MB	144MB	3	168-pin DIMM	70 ns	32, 64, 128 MB	1
Umax SuperMac S900/150	16MB	16-64	1GB	8	168-pin DIMM	70 ns	32, 64, 128 MB	2
Umax SuperMac S900/180	16MB	16-64	1GB	8	168-pin DIMM	70 ns	32, 64, 128 MB	2
Umax SuperMac S900/180DP	16MB	16-64	1GB	8	168-pin DIMM	70 ns	32, 64, 128 MB	2
Umax SuperMac S900/200	16MB	16-64	1GB	8	168-pin DIMM	70 ns	32, 64, 128 MB	2
Umax SuperMac S900/200DP	16MB	16-64	1GB	8	168-pin DIMM	70 ns	32, 64, 128 MB	2
Umax SuperMac S900/225	16MB	16-64	1GB	8	168-pin DIMM	70 ns	32, 64, 128 MB	2
Umax SuperMac S900/233	16MB	16-64	1GB	8	168-pin DIMM	70 ns	32, 64, 128 MB	2
Umax SuperMac S900/250	16MB	16-64	1GB	8	168-pin DIMM	70 ns	32, 64, 128 MB	2
Umax SuperMac S900/250DP	16MB	16-64	1GB	8	168-pin DIMM	70 ns	32, 64, 128 MB	2
Umax SuperMac S900/G3	16MB	16-64	1GB	8	168-pin DIMM	70 ns	32, 64, 128 MB	2
Umax SuperMac S910	16MB	16-64	1GB	8	168-pin DIMM	70 ns	32, 64, 128 MB	2
Workgroup Server 60	8 MB	8 MB	68 MB	4	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Workgroup Server 60 (50/25 MHz)	8 MB	8 MB	68 MB	4	72-pin SIMM	80 ns	4, 8, 16, 32 MB	1
Workgroup Server 6150	8 MB	8 MB	72 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Workgroup Server 6150/66	8M B	16 MB	72 MB	2	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Workgroup Server 7250/120	none	16 MB	256 MB	4	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Workgroup Server 7350/180	none	48 MB	512 MB	8	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Workgroup Server 80	8 MB	8 MB	136 MB	4	72-pin SIMM	60 ns	4, 8, 16, 32 MB	1
Workgroup Server 8150	8 MB	8 MB	264 MB	8	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Workgroup Server 8150/110	8 MB	16 MB	264 MB	8	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Workgroup Server 8550/132	none	24 MB	512 MB	8	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Workgroup Server 8550/200	none	32 MB	512 MB	8	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Workgroup Server 9150	8 MB	8 MB	264 M B	8	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Workgroup Server 9150/120	8 MB	16 MB	264 MB	8	72-pin SIMM	80 ns	4, 8, 16, 32 MB	2
Workgroup Server 95	none	8 MB	256 MB	16	30-pin SIMM	80 ns	1, 4, 8, 16 MB	4
Workgroup Server 9650/233	none	64 MB	768 MB	12	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Workgroup Server 9650/350	none	64 MB	768 MB	12	168-pin DIMM	70 ns	8, 16, 32, 64 MB	1
Xserve	none	256MB	2GB	4	PC2100 DDR	10 ns	128, 256, 512 MB	1